SIEMENS

Data sheet

3RV2321-4BC10



Circuit breaker size S0 for starter combination Rated current 20 A N-release 260 A screw terminal Standard switching capacity

product brand name	SIRIUS			
product designation	Circuit breaker			
design of the product	For starter combinations			
product type designation	3RV2			
General technical data				
size of the circuit-breaker	SO			
size of contactor can be combined company-specific	S00, S0			
product extension auxiliary switch	Yes			
power loss [W] for rated value of the current				
 at AC in hot operating state 	10.5 W			
 at AC in hot operating state per pole 	3.5 W			
insulation voltage with degree of pollution 3 at AC rated value	690 V			
surge voltage resistance rated value	6 kV			
shock resistance according to IEC 60068-2-27	25g / 11 ms			
mechanical service life (switching cycles)				
 of the main contacts typical 	100 000			
 of auxiliary contacts typical 	100 000			
electrical endurance (switching cycles) typical	100 000			
reference code according to IEC 81346-2	Q			
Substance Prohibitance (Date)	10/01/2009			
Ambient conditions				
installation altitude at height above sea level maximum	2 000 m			
ambient temperature				
 during operation 	-20 +60 °C			
 during storage 	-50 +80 °C			
 during transport 	-50 +80 °C			
relative humidity during operation	10 95 %			
Main circuit				
number of poles for main current circuit	3			
operating voltage				
 rated value 	20 690 V			
 at AC-3 rated value maximum 	690 V			
 at AC-3e rated value maximum 	690 V			
operating frequency rated value	50 60 Hz			
operational current rated value	20 A			
operational current				
 at AC-3 at 400 V rated value 	20 A			
 at AC-3e at 400 V rated value 	20 A			

operating power	
• at AC-3	
— at 230 V rated value	5.5 kW
— at 400 V rated value	7.5 kW
— at 500 V rated value	11 kW
— at 690 V rated value	15 kW
• at AC-3e	
— at 230 V rated value	5.5 kW
— at 400 V rated value	7.5 kW
— at 500 V rated value	11 kW
— at 690 V rated value	15 kW
operating frequency	
 at AC-3 maximum 	15 1/h
• at AC-3e maximum	15 1/h
Auxiliary circuit	
number of NC contacts for auxiliary contacts	0
number of NO contacts for auxiliary contacts	0
number of CO contacts for auxiliary contacts	0
Protective and monitoring functions	
product function	
 ground fault detection 	No
 phase failure detection 	No
breaking capacity maximum short-circuit current (lcu)	
 at AC at 240 V rated value 	100 kA
 at AC at 400 V rated value 	55 kA
 at AC at 500 V rated value 	10 kA
at AC at 690 V rated value	4 kA
breaking capacity operating short-circuit current (Ics) at AC	
• at 240 V rated value	100 kA
• at 400 V rated value	25 kA
• at 500 V rated value	5 kA
• at 690 V rated value	2 kA
response value current of instantaneous short-circuit trip unit	260 A
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	
• at 480 V rated value	20 A
 at 600 V rated value 	20 A
yielded mechanical performance [hp]	
 for single-phase AC motor 	
— at 110/120 V rated value	1.5 hp
— at 230 V rated value	3 hp
 for 3-phase AC motor 	
— at 200/208 V rated value	7.5 hp
— at 220/230 V rated value	5 hp
— at 460/480 V rated value	10 hp
Short-circuit protection	
product function short circuit protection	Yes
design of the short-circuit trip	magnetic
design of the fuse link for IT network for short-circuit protection of the main circuit	
• at 400 V	gL/gG 63 A
● at 500 V	gL/gG 50 A
• at 690 V	gL/gG 50 A
Installation/ mounting/ dimensions	
mounting position	any
fastening method	screw and snap-on mounting onto 35 mm standard mounting rail
	according to DIN EN 60715
height	97 mm

width	45 mm		
depth	97 mm		
required spacing			
 for grounded parts at 400 V 			
— downwards	30 mm		
— upwards	30 mm		
— at the side	9 mm		
• for live parts at 400 V			
— downwards	30 mm		
— upwards	30 mm		
— at the side	9 mm		
	5 1111		
• for grounded parts at 500 V	30 mm		
— downwards	30 mm		
— upwards			
— at the side	9 mm		
• for live parts at 500 V			
— downwards	30 mm		
— upwards	30 mm		
— at the side	9 mm		
 for grounded parts at 690 V 			
— downwards	50 mm		
— upwards	50 mm		
— backwards	0 mm		
— at the side	30 mm		
— forwards	0 mm		
 for live parts at 690 V 			
— downwards	50 mm		
— upwards	50 mm		
— backwards	0 mm		
— at the side	30 mm		
— forwards	0 mm		
Connections/ Terminals			
type of electrical connection			
for main current circuit	screw-type terminals		
	screw-type terminals Top and bottom		
• for main current circuit arrangement of electrical connectors for main current circuit			
for main current circuit arrangement of electrical connectors for main current			
• for main current circuit arrangement of electrical connectors for main current circuit			
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections	Top and bottom 2x (1 2.5 mm²), 2x (2.5 10 mm²)		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections • for main contacts	Top and bottom		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts — solid or stranded	Top and bottom 2x (1 2.5 mm²), 2x (2.5 10 mm²)		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections • for main contacts — solid or stranded — finely stranded with core end processing	Top and bottom 2x (1 2.5 mm²), 2x (2.5 10 mm²) 2x (1 2.5 mm²), 2x (2.5 6 mm²), 1x 10 mm²		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections • for main contacts — solid or stranded — finely stranded with core end processing • at AWG cables for main contacts	Top and bottom 2x (1 2.5 mm²), 2x (2.5 10 mm²) 2x (1 2.5 mm²), 2x (2.5 6 mm²), 1x 10 mm²		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections • for main contacts — solid or stranded — finely stranded with core end processing • at AWG cables for main contacts tightening torque	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8)		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections • for main contacts — solid or stranded — finely stranded with core end processing • at AWG cables for main contacts tightening torque • for main contacts with screw-type terminals	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m Diameter 5 to 6 mm		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts — solid or stranded — finely stranded with core end processing • at AWG cables for main contacts tightening torque • for main contacts with screw-type terminals design of screwdriver shaft size of the screwdriver tip	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m Diameter 5 to 6 mm		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts solid or stranded finely stranded with core end processing • at AWG cables for main contacts tightening torque • for main contacts with screw-type terminals design of screwdriver shaft size of the screwdriver tip design of the thread of the connection screw	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m Diameter 5 to 6 mm Pozidriv size 2		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts — solid or stranded — finely stranded with core end processing • at AWG cables for main contacts tightening torque • for main contacts with screw-type terminals design of screwdriver shaft size of the screwdriver tip design of the thread of the connection screw • for main contacts	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m Diameter 5 to 6 mm Pozidriv size 2		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts solid or stranded finely stranded with core end processing at AWG cables for main contacts tightening torque for main contacts with screw-type terminals design of screwdriver shaft size of the screwdriver tip design of the thread of the connection screw for main contacts 	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m Diameter 5 to 6 mm Pozidriv size 2		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts solid or stranded finely stranded with core end processing at AWG cables for main contacts tightening torque for main contacts with screw-type terminals design of screwdriver shaft size of the screwdriver tip design of the thread of the connection screw for main contacts B10 value	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m Diameter 5 to 6 mm Pozidriv size 2 M4		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m Diameter 5 to 6 mm Pozidriv size 2 M4		
for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts solid or stranded finely stranded with core end processing at AWG cables for main contacts tightening torque for main contacts with screw-type terminals design of screwdriver shaft size of the screwdriver tip design of the thread of the connection screw 	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m Diameter 5 to 6 mm Pozidriv size 2 M4 5 000		
 for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts solid or stranded finely stranded with core end processing at AWG cables for main contacts tightening torque for main contacts with screw-type terminals design of screwdriver shaft size of the screwdriver tip design of the thread of the connection screw for main contacts B10 value with high demand rate according to SN 31920 proportion of dangerous failures with low demand rate according to SN 31920 with high demand rate according to SN 31920 with high demand rate according to SN 31920 	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m Diameter 5 to 6 mm Pozidriv size 2 M4 5 000 50 %		
 for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts solid or stranded finely stranded with core end processing at AWG cables for main contacts tightening torque for main contacts with screw-type terminals design of screwdriver shaft size of the screwdriver tip design of the thread of the connection screw for main contacts B10 value with high demand rate according to SN 31920 	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m Diameter 5 to 6 mm Pozidriv size 2 M4 5 000 50 %		
 for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts solid or stranded finely stranded with core end processing at AWG cables for main contacts tightening torque for main contacts with screw-type terminals design of screwdriver shaft size of the screwdriver tip design of the thread of the connection screw for main contacts size of the screwdriver tip design of the thread of the connection screw for main contacts with high demand rate according to SN 31920 proportion of dangerous failures with low demand rate according to SN 31920 with high demand rate according to SN 31920 failure rate [FIT] with low demand rate according to SN 31920 	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m Diameter 5 to 6 mm Pozidriv size 2 M4 5 000 50 % 50 %		
 for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts solid or stranded finely stranded with core end processing at AWG cables for main contacts tightening torque for main contacts with screw-type terminals design of screwdriver shaft size of the screwdriver tip design of the thread of the connection screw for main contacts B10 value with high demand rate according to SN 31920 proportion of dangerous failures with low demand rate according to SN 31920 with low demand rate according to SN 31920 to value for proof test interval or service life according to IEC	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m Diameter 5 to 6 mm Pozidriv size 2 M4 5 000 50 % 50 % 50 %		
 for main current circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts solid or stranded finely stranded with core end processing at AWG cables for main contacts tightening torque for main contacts with screw-type terminals design of screwdriver shaft size of the screwdriver tip design of the thread of the connection screw for main contacts Safety related data B10 value with high demand rate according to SN 31920 proportion of dangerous failures with low demand rate according to SN 31920 failure rate [FIT] with low demand rate according to SN 31920 T1 value for proof test interval or service life according to IEC 61508 	Top and bottom 2x (1 2.5 mm ²), 2x (2.5 10 mm ²) 2x (1 2.5 mm ²), 2x (2.5 6 mm ²), 1x 10 mm ² 2x (16 12), 2x (14 8) 2 2.5 N·m Diameter 5 to 6 mm Pozidriv size 2 M4 5 000 50 % 50 % 50 FIT 10 y		

display version for sw	vitching status	Hand	dle			
Certificates/ approval	ls					
General Product Ap	oproval					
	<u>Confirmation</u>			<u>KC</u>	EHC	
Declaration of Cont	formity	Test Certificates		Marine / Shipping		
UK CA	C C EG-Konf.	<u>Type Test Certific-</u> ates/Test Report	<u>Special Test Certific-</u> <u>ate</u>	ABS	BUREAU VERITAS	
Marine / Shipping					other	
	Lloyds Register uis	PRS	RINA	RMRS	<u>Confirmation</u>	
other	Railway					
UDE VDE	<u>Confirmation</u>	Vibration and Shock				
Further information Information- and Downloadcenter (Catalogs, Brochures,) https://www.siemens.com/ic10 Industry Mall (Online ordering system) https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RV2321-4BC10 Cax online generator http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RV2321-4BC10 Service&Support (Manuals, Certificates, Characteristics, FAQs,) https://support.industry.siemens.com/cs/ww/en/ps/3RV2321-4BC10 Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros,) http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RV2321-4BC10⟨=en Characteristic: Tripping characteristics, I²t, Let-through current https://support.industry.siemens.com/cs/ww/en/ps/3RV2321-4BC10/char Further characteristics (e.g. electrical endurance, switching frequency) http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RV2321-4BC10&objecttype=14&gridview=view1						

last modified:

6/25/2022 🖸