SIEMENS

Data sheet

3RA2115-4AA18-1AP6



Fuseless motor starter Direct start 600VAC Size S00 11-16Amp 220/240VAC 50/60HZ screw connection For screw mounting Or 35 mm rail-mounting Type of coordination 1 1NO+1NC (MSP) 1NO (contactor)

product brand name	SIRIUS
product designation	non-fused motor starter 3RA2
design of the product	direct starter
manufacturer's article number	
of the supplied contactor	<u>3RT2018-1AP61</u>
 of the supplied contactor of the supplied circuit-breakers 	3RV2011-4AA15
of the supplied link module	3RA1921-1DA00
General technical data	
size of the circuit-breaker	S00
size of load feeder	S00
	Yes
product extension auxiliary switch	690 V
insulation voltage with degree of pollution 3 at AC rated value	090 V
degree of pollution	3
surge voltage resistance rated value	6 kV
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (switching cycles) of contactor typical	30 000 000
type of assignment	1
Ambient conditions	
ambient temperature	
 during operation 	-20 +60 °C
 during storage 	-50 +80 °C
 during transport 	-55 +80 °C
Main circuit	
number of poles for main current circuit	3
design of the switching contact	electromechanical
adjustable current response value current of the current-dependent overload release	11 16 A
operating voltage	
 rated value 	690 V
 at AC-3 rated value maximum 	690 V
	000 1
operating frequency rated value	50 60 Hz
operating frequency rated value operational current at AC-3 at 400 V rated value	
	50 60 Hz
operational current at AC-3 at 400 V rated value	50 60 Hz
operational current at AC-3 at 400 V rated value operating power at AC-3	50 60 Hz 15.5 A
operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value	50 60 Hz 15.5 A 7 500 W
operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value	50 60 Hz 15.5 A 7 500 W

a of EO Liz rotod vicinia	107 040 \/
at 50 Hz rated value	187 242 V
• at 60 Hz rated value	240 V
at 60 Hz rated value	192 264 V
apparent holding power of magnet coil at AC	6.5 VA
inductive power factor with the holding power of the coil	0.25
Auxiliary circuit	
number of NC contacts for auxiliary contacts	1
number of NO contacts for auxiliary contacts	2
Protective and monitoring functions	
trip class	CLASS 10
design of the overload release	thermal (bimetallic)
response value current of instantaneous short-circuit trip unit	208 A
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	
 at 480 V rated value 	14 A
at 600 V rated value	11 A
yielded mechanical performance [hp]	
 for single-phase AC motor 	
— at 110/120 V rated value	1 hp
— at 230 V rated value	2 hp
 for 3-phase AC motor 	
— at 200/208 V rated value	3 hp
— at 220/230 V rated value	5 hp
— at 460/480 V rated value	10 hp
— at 575/600 V rated value	10 hp
Short-circuit protection	
product function short circuit protection	Yes
design of the short-circuit trip	magnetic
conditional short-circuit current (Iq)	
 at 400 V according to IEC 60947-4-1 rated value 	153 000 A
Installation/ mounting/ dimensions	
mounting position	vertical
fastening method	Snap-mounted to DIN rail or screw-mounted with additional push-in lug
height	167.2 mm
width	45 mm
width depth	45 mm 97.1 mm
depth	
depth required spacing	
depth required spacing • for grounded parts	97.1 mm
depth required spacing • for grounded parts — forwards	97.1 mm 0 mm
depth required spacing • for grounded parts — forwards — backwards	97.1 mm 0 mm 0 mm
depth required spacing • for grounded parts — forwards — backwards — upwards	97.1 mm 0 mm 0 mm 20 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side	97.1 mm 0 mm 0 mm 20 mm 9 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards	97.1 mm 0 mm 0 mm 20 mm 9 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards	97.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards • for live parts — upwards — upwards	97.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 20 mm 20 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — downwards — forwards — downwards — backwards — upwards — downwards	97.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 0 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards • for live parts — upwards — upwards	97.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 20 mm 20 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — downwards — forwards — downwards — backwards — upwards — downwards	97.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 20 mm 20 mm 10 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — of upwards — at the side — downwards • for live parts — forwards — upwards — upwards — at the side	97.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 20 mm 20 mm 10 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — ownwards • for live parts — downwards — at the side — ownwards — at the side — ownwards — at the side — downwards — at the side Connections/ Terminals	97.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 20 mm 10 mm 9 mm 10 mm 9 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — ownwards • for live parts — forwards — at the side — downwards — at the side Connections/ Terminals type of electrical connection for main current circuit	97.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 0 mm 20 mm 10 mm 20 mm 10 mm 9 mm 20 mm 10 mm 20 mm 10 mm 20 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — ownwards • for live parts — ownwards — upwards — upwards — downwards — at the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded • at AWG cables for main contacts	97.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 0 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — ownwards • for live parts — forwards — upwards — upwards — at the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded	97.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 20 mm 10 mm 20 mm 10 mm 9 mm 20 mm 10 mm 20 mm 10 mm 20 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — ownwards • for live parts — ownwards — upwards — upwards — downwards — at the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded • at AWG cables for main contacts connectable conductor cross-section for main contacts	97.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 0 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm
depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — ownwards • for live parts — forwards — backwards — upwards — downwards — upwards — at the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded • at AWG cables for main contacts connectable conductor cross-section for main contacts finely stranded with core end processing	97.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 0 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm

proportion of danger	rous failures with high den	and rate 7	3 %			
proportion of dangerous failures with high demand rate according to SN 31920			13 %			
protection class IP on the front according to IEC 60529		to IEC IF	IP20			
touch protection on the front according to IEC 60529			finger-safe, for vertical contact from the front			
Certificates/ approva	als					
General Product A	opproval			For use in hazard- ous locations	Declaration of Conformity	
(SP) CM	<u>Confirmation</u>		EHC	K ATEX	CE EG-Konf.	
Declaration of Conformity	Test Certificates		Marine / Shipping			
UK CA	<u>Type Test Certific-</u> ates/Test Report	<u>Special Test Certif</u> <u>ate</u>	iC-	BUREAU VERITAS	Hoyd's Register uis	
Marine / Shipping				other	Railway	
PRS	RINA	RMRS RMRS	DNV-GL	<u>Confirmation</u>	Vibration and Shock	
urther information Information- and Downloadcenter (Catalogs, Brochures,)						
https://www.siemens.com/ic10 Industry Mall (Online ordering system) https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2115-4AA18-1AP6 Cax online generator						
http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2115-4AA18-1AP6						
	Manuals, Certificates, Cl stry.siemens.com/cs/ww/e					
Image database (pr	roduct images, 2D dimer	nsion drawings, 3	D models, device circuit		cros,)	
Characteristic: Trip https://support.indus	pping characteristics, I ² t, stry.siemens.com/cs/ww/e	, Let-through curr n/ps/3RA2115-4AA	<u>18-1AP6/char</u>	lg=en		
Further characteristics (e.g. electrical endurance, switching frequency) http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2115-4AA18-1AP6&objecttype=14&gridview=view1						

last modified:

12/15/2020 🖸