
KEMET Part Number: CWR11KH685KC

(T492D685K025CH)



T492 CWR11, Tantalum, MnO2 Tantalum, Military/High Reliability, 6.8 uF, 10%, 25 VDC, SMD, MnO2, Molded, Military Equivalent, C (0.01%/1000 Hrs), 1.4 Ohms, 7343, Height Max = 3.1mm



Dimensions		
Footprint	7343	
L	7.3mm +/-0.3mm	
W	4.3mm +/-0.3mm	
Н	2.8mm +/-0.3mm	
Т	0.13mm REF	
S	1.3mm +/-0.3mm	
F	2.4mm +/-0.1mm	
В	0.5mm +/-0.15mm	
E	3.5mm REF	
G	3.5mm REF	
K	1mm MIN	
Р	0.5mm MIN	
R	1mm REF	
Х	0.1mm +/-0.1mm	

Packaging Specifications		
Weight:	412.33 mg	
Packaging:	T&R, 178mm	
Packaging Quantity:	500	

General Information		
Series:	T492 CWR11	
Dielectric:	MnO2 Tantalum	
Style:	SMD Chip	
Description:	SMD, MnO2, Molded, Military Equivalent	
RoHS:	No	
Prop 65:	A WARNING: Cancer and reproductive harm - www.p65warnings.ca.gov.	
REACH:	SVHC (Pb – CAS 7439-92-1)	
SCIP Number:	1dd2e1b8-26dd-4d52-927c-6f9d519011	зa
Termination:	Solder Coated	
Qualifications:	MIL-PRF-55365/8, CWR11 Style	
AEC-Q200:	No	
Notes:	Note: When Option C Is Selected For Lead Material, Add An Additional 0.38mm To The Tolerances For "L", "W", "H", "K", "F" And "S".	
MSL:	1	

Specifications		
Capacitance:	6.8 uF	
Capacitance Tolerance:	10%	
Voltage DC:	25 VDC (85C), 16.75 VDC (125C)	
Temperature Range:	-55/+125°C	
Rated Temperature:	85°C	
Dissipation Factor:	6% 120Hz 25C	
Failure Rate:	C (0.01%/1000 Hrs)	
Resistance:	1.4 Ohms (100kHz 25C)	
Leakage Current:	1.7 uA (5min 25°C)	
Testing and Reliability:	Standard Testing Only	

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.

