Decade Counter

The MC14017B is a five-stage Johnson decade counter with built-in code converter. High speed operation and spike-free outputs are obtained by use of a Johnson decade counter design. The ten decoded outputs are normally low, and go high only at their appropriate decimal time period. The output changes occur on the positive-going edge of the clock pulse. This part can be used in frequency division applications as well as decade counter or decimal decode display applications.

Features

- Fully Static Operation
- DC Clock Input Circuit Allows Slow Rise Times
- Carry Out Output for Cascading
- Divide-by-N Counting
- Supply Voltage Range = 3.0 Vdc to 18 Vdc
- Capable of Driving Two Low–Power TTL Loads or One Low–Power Schottky TTL Load Over the Rated Temperature Range
- Pin-for-Pin Replacement for CD4017B
- Triple Diode Protection on All Inputs
- NLV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC–Q100 Qualified and PPAP Capable
- This Device is Pb-Free and is RoHS Compliant

MAXIMUM RATINGS (Voltages Referenced to V_{SS})

	`		
Symbol	Parameter	Value	Unit
V _{DD}	DC Supply Voltage Range	–0.5 to +18.0	V
V _{in} , V _{out}	Input or Output Voltage Range (DC or Transient)	–0.5 to V _{DD} + 0.5	V
I _{in} , I _{out}	Input or Output Current (DC or Transient) per Pin	±10	mA
P _D	Power Dissipation, per Package (Note 1)	500	mW
T _A	Ambient Temperature Range	-55 to +125	°C
T _{stg}	Storage Temperature Range	-65 to +150	°C
ΤL	Lead Temperature (8–Second Soldering)	260	°C

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

1. Temperature Derating: "D/DW" Packages: -7.0 mW/°C From 65°C To 125°C

This device contains protection circuitry to guard against damage due to high static voltages or electric fields. However, precautions must be taken to avoid applications of any voltage higher than maximum rated voltages to this high–impedance circuit. For proper operation, V_{in} and V_{out} should be constrained to the range $V_{SS} \leq (V_{in} \text{ or } V_{out}) \leq V_{DD}.$

Unused inputs must always be tied to an appropriate logic voltage level (e.g., either V_{SS} or V_{DD}). Unused outputs must be left open.



ON Semiconductor®

http://onsemi.com




D SUFFIX CASE 751B

PIN ASSIGNMENT

Q5 [16	V _{DD}
Q1 [2	15] RESET
Q0 [3	14] сгоск
Q2 [4	13	
Q6 [5	12] C _{out}
Q7 [6	11] Q9
Q3 [7	10] Q4
v _{ss} [8	9] Q8

MARKING DIAGRAM



ORDERING INFORMATION


See detailed ordering and shipping information in the package dimensions section on page 7 of this data sheet.

FUNCTIONAL TRUTH TABLE (Positive Logic)


Clock	Clock Enable	Reset	Decode Output=n
0	Х	0	n
X	1	0	n
X	Х	1	Q0
	0	0	n+1
~	Х	0	n
Х		0	n
1	~	0	n+1

X = Don't Care. If n < 5 Carry = "1", Otherwise = "0".

BLOCK DIAGRAM



LOGIC DIAGRAM



MC14017B

ELECTRICAL CHARACTERISTICS	3 (Voltages Referenced to V _{SS})
----------------------------	--

				-55	S°C		25°C		125	S°C	
Characteristic		Symbol	V _{DD} Vdc	Min	Max	Min	Typ (Note 2)	Мах	Min	Мах	Unit
Output Voltage	"0" Level	V _{OL}	5.0	_	0.05	_	0	0.05	_	0.05	Vdc
$V_{in} = V_{DD} \text{ or } 0$		01	10	-	0.05	-	0	0.05	_	0.05	
			15	-	0.05	-	0	0.05	-	0.05	
	"1" Level	V _{OH}	5.0	4.95	_	4.95	5.0	_	4.95	_	Vdc
$V_{in} = 0 \text{ or } V_{DD}$		011	10	9.95	-	9.95	10	_	9.95	_	
			15	14.95	-	14.95	15	-	14.95	-	
Input Voltage	"0" Level	VIL									Vdc
(V _O = 4.5 or 0.5 Vdc)			5.0	-	1.5	-	2.25	1.5	-	1.5	
(V _O = 9.0 or 1.0 Vdc)			10	-	3.0	-	4.50	3.0	-	3.0	
(V _O = 13.5 or 1.5 Vdc)			15	-	4.0	-	6.75	4.0	-	4.0	
	"1" Level	V _{IH}									Vdc
(V _O = 0.5 or 4.5 Vdc)			5.0	3.5	-	3.5	2.75	-	3.5	-	
$(V_0 = 1.0 \text{ or } 9.0 \text{ Vdc})$			10	7.0	-	7.0	5.50	-	7.0	-	
$(V_0 = 1.5 \text{ or } 13.5 \text{ Vdc})$			15	11	-	11	8.25	-	11	-	
Output Drive Current		I _{OH}									mAdo
(V _{OH} = 2.5 Vdc)	Source		5.0	-3.0	-	-2.4	-4.2	-	-1.7	-	
(V _{OH} = 4.6 Vdc)			5.0	-0.64	-	-0.51	-0.88	-	-0.36	-	
(V _{OH} = 9.5 Vdc)			10	-1.6	-	-1.3	-2.25	-	-0.9	-	
(V _{OH} = 13.5 Vdc)			15	-4.2	-	-3.4	-8.8	-	-2.4	-	
(V _{OL} = 0.4 Vdc)	Sink	I _{OL}	5.0	0.64	-	0.51	0.88	_	0.36	_	mAdo
$(V_{OL} = 0.5 \text{ Vdc})$			10	1.6	-	1.3	2.25	-	0.9	-	
(V _{OL} = 1.5 Vdc)			15	4.2	-	3.4	8.8	-	2.4	-	
Input Current		l _{in}	15	-	±0.1	-	±0.00001	±0.1	-	±1.0	μAdc
Input Capacitance (V _{in} = 0)		C _{in}	-	-	-	-	5.0	7.5	-	-	pF
Quiescent Current		I _{DD}	5.0	-	5.0	-	0.005	5.0	-	150	μAdc
(Per Package)			10	-	10	-	0.010	10	-	300	1
			15	-	20	-	0.015	20	-	600	
Total Supply Current (Notes 3 & 4)		Ι _Τ	5.0				.27 μA/kHz) 1				μAdc
(Dynamic plus Quiescent,			10				.55 μA/kHz) 1				
Per Package)			15			l _T = (0	.83 μA/kHz) 1	f + I _{DD}			
$(C_L = 50 \text{ pF on all output})$	uts, all										1
buffers switching)											

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.
2. Data labelled "Typ" is not to be used for design purposes but is intended as an indication of the IC's potential performance.
3. The formulas given are for the typical characteristics only at 25°C.
4. To calculate total supply current at loads other than 50 pF:

 $I_T(C_L) = I_T(50 \text{ pF}) + (C_L - 50) \text{ Vfk}$

where: I_T is in μ A (per package), C_L in pF, V = (V_{DD} - V_{SS}) in volts, f in kHz is input frequency, and k = 0.0011.

MC14017B

SWITCHING CHARACTERISTICS (Note 5) (C_L = 50 pF, T_A = 25°C)

Characteristic	Symbol	V _{DD} Vdc	Min	Typ (Note 6)	Max	Unit
Output Rise and Fall Time t_{TLH} , $t_{THL} = (1.5 \text{ ns/pF}) C_L + 25 \text{ ns}$ t_{TLH} , $t_{THL} = (0.75 \text{ ns/pF}) C_L + 12.5 \text{ ns}$ t_{TLH} , $t_{THL} = (0.55 \text{ ns/pF}) C_L + 9.5 \text{ ns}$	t _{TLH} , t _{THL}	5.0 10 15	- - -	100 50 40	200 100 80	ns
Propagation Delay Time Reset to Decode Output t_{PLH} , $t_{PHL} = (1.7 \text{ ns/pF}) C_L + 415 \text{ ns}$ t_{PLH} , $t_{PHL} = (0.66 \text{ ns/PF}) C_L + 197 \text{ ns}$ t_{PLH} , $t_{PHL} = (0.5 \text{ ns/pF}) C_L + 150 \text{ ns}$	t _{PLH} , t _{PHL}	5.0 10 15	- - -	500 230 175	1000 460 350	ns
Propagation Delay Time Clock to C_{out} t_{PLH} , $t_{PHL} = (1.7 \text{ ns/pF}) C_L + 315 \text{ ns}$ t_{PLH} , $t_{PHL} = (0.66 \text{ ns/pF}) C_L + 142 \text{ ns}$ t_{PLH} , $t_{PHL} = (0.5 \text{ ns/pF}) C_L + 100 \text{ ns}$	t _{PLH} , tPHL	5.0 10 15	- - -	400 175 125	800 350 250	ns
Propagation Delay Time Clock to Decode Output t_{PLH} , $t_{PHL} = (1.7 \text{ ns/pF}) C_L + 415 \text{ ns}$ t_{PLH} , $t_{PHL} = (0.66 \text{ ns/pF}) C_L + 197 \text{ ns}$ t_{PLH} , $t_{PHL} = (0.5 \text{ ns/pF}) C_L + 150 \text{ ns}$	t _{PLH} , t _{PHL}	5.0 10 15	- - -	500 230 175	1000 460 350	ns
Turn–Off Delay Time Reset to C_{out} $t_{PLH} = (1.7 \text{ ns/pF}) C_L + 315 \text{ ns}$ $t_{PLH} = (0.66 \text{ ns/pF}) C_L + 142 \text{ ns}$ $t_{PLH} = (0.5 \text{ ns/pF}) C_L + 100 \text{ ns}$	t _{PLH}	5.0 10 15	- - -	400 175 125	800 350 250	ns
Clock Pulse Width	t _{w(H)}	5.0 10 15	250 100 75	125 50 35	- - -	ns
Clock Frequency	f _{cl}	5.0 10 15		5.0 12 16	2.0 5.0 6.7	MHz
Reset Pulse Width	t _{w(H)}	5.0 10 15	500 250 190	250 125 95	- - -	ns
Reset Removal Time	t _{rem}	5.0 10 15	750 275 210	375 135 105	- - -	ns
Clock Input Rise and Fall Time	t _{TLH} , t _{THL}	5.0 10 15		No Limit		-
Clock Enable Setup Time	t _{su}	5.0 10 15	350 150 115	175 75 52		ns
Clock Enable Removal Time	t _{rem}	5.0 10 15	420 200 140	260 100 70	- - -	ns

The formulas given are for the typical characteristics only at 25°C.
 Data labelled "Typ" is not to be used for design purposes but is intended as an indication of the IC's potential performance.




Figure 1. Typical Output Source and Output Sink Characteristics Test Circuit




Figure 2. Typical Power Dissipation Test Circuit

MC14017B

APPLICATIONS INFORMATION

Figure 3 shows a technique for extending the number of decoded output states for the MC14017B. Decoded outputs are sequential within each stage and from stage to stage, with no dead time (except propagation delay).





Figure 3. Counter Expansion





ORDERING INFORMATION

Device	Package	Shipping [†]
MC14017BDG	SOIC-16 (Pb-Free)	48 Units / Rail
NLV14017BDG*	SOIC-16 (Pb-Free)	48 Units / Rail
MC14017BDR2G	SOIC-16 (Pb-Free)	2500 Units / Tape & Reel
NLV14017BDR2G*	SOIC-16 (Pb-Free)	2500 Units / Tape & Reel

+For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.
 *NLV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC–Q100 Qualified and PPAP

Capable.





DIMENSIONS: MILLIMETERS

DOCUMENT NUMBER:	98ASB42566B Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.					
DESCRIPTION:	SOIC-16		PAGE 1 OF 1			
ON Semiconductor and 🕕 are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding						

ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. ON Semiconductor does not convey any license under its patent rights nor the rights of others.

onsemi, ONSEMI, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and calcular performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

TECHNICAL SUPPORT

onsemi Website: www.onsemi.com

Email Requests to: orderlit@onsemi.com

North American Technical Support: Voice Mail: 1 800-282-9855 Toll Free USA/Canada Phone: 011 421 33 790 2910

Europe, Middle East and Africa Technical Support: Phone: 00421 33 790 2910 For additional information, please contact your local Sales Representative