

Technical Data Sheet

0603 Package Chip LED (0.8mm Height)

19-21/G6W-BL2N1L/3T

Features

- Package in 8mm tape on 7" diameter reel.
- Compatible with automatic placement equipment.
- Compatible with infrared and vapor phase reflow solder process.
- Mono-color type.
- Pb Free.

Descriptions

- The 19-21 SMD Taping is much smaller than lead frame type components, thus enable smaller board size, higher packing density, reduced storage space and finally smaller equipment to be obtained.
- Besides, lightweight makes them ideal for miniature applications. etc.

Applications

- Automotive: backlighting in dashboard and switch.
- Telecommunication: indicator and backlighting in telephone and fax.
- Flat backlight for LCD, switch and symbol.
- General use.

Device Selection Guide

D (1)			
Part No.	Material	Emitted Color	Lens Color
19-21/G6W-BL2N1L/3T	AlGaInP	Brilliant Yellow Green	White Diffused



Everlight Electronics Co., Ltd. Device No:SZDSE-191-G04

http://www.everlight.com


Prepared date: 29-Dec-2004

Rev. 1


Page: 1 of 10

Prepared by: Wu xiaowei


Package Outline Dimensions







For reflow soldering



Note: The tolerances unless mentioned is ± 0.1 mm ,Unit = mm

Everlight Electronics Co., Ltd. Device No:SZDSE-191-G04 http://www.everlight.com

Rev. 1

Page: 2 of 10

Prepared date: 29-Dec-2004

Prepared by: Wu xiaowei



Absolute Maximum Ratings (Ta=25°C)

Parameter	Symbol	Rating	Unit
Reverse Voltage	VR	5	V
Forward Current	${f I}_{f F}$	25	mA
Operating Temperature	Topr	-40 ~ +85	$^{\circ}\!\mathbb{C}$
Storage Temperature	Tstg	-40 ~ +90	$^{\circ}$
Soldering Temperature	Tsol	260(for 5 second)	$^{\circ}\!\mathbb{C}$
Electrostatic Discharge	ESD	2000	V
Power Dissipation	Pd	60	mW
Peak Forward Current (Duty 1/10 @1KHz)	IFP	60	mA

Electro-Optical Characteristics (Ta=25 $^{\circ}$ C)

Parameter	Symbol	Min.	Тур.	Max.	Unit	Condition	
Luminous Intensity	Iv	14.5		36.0	mcd		
Viewing Angle	2 \theta 1/2		110		deg		
Peak Wavelength	λр		575		nm		
Dominant Wavelength	λd	567.5		575.5	nm	IF=20mA	
Spectrum Radiation Bandwidth	Δλ		20		nm		
Forward Voltage	VF	1.70		2.30	V		
Reverse Current	IR			10	μΑ	VR=5V	

Notes:

- 1. Tolerance of Luminous Intensity ±10%
- 2.Tolerance of Dominant Wavelength ±1nm
- 3. Tolerance of Forward Voltage $\pm 0.05V$

Everlight Electronics Co., Ltd. http://www.everlight.com Rev. 1 Page: 3 of 10 Device No:SZDSE-191-G04 Prepared date: 29-Dec-2004 Prepared by: Wu xiaowei

Bin Range Of Dom. Wavelength

Group	Bin	Min	Max	Unit	Condition
В	CC15	567.5	569.5		IF=20mA
	CC16	569.5	571.5		
	CC17	571.5	573.5	nm	
	CC18	573.5	575.5		

Bin Range Of Luminous Intensity

Bin	Min	Max	Unit	Condition
L2	14.5	18.0		IF=20mA
M1	18.0	22.5	,	
M2	22.5	28.5	mcd	
N1	28.5	36.0		

Bin Range Of Forward Voltage


Groups	Bin	Min	Max	Unit	Condition
L	19	1.70	1.80		IF=20mA
	20	1.80	1.90	V	
	21	1.90	2.00		
	22	2.00	2.10		
	23	2.10	2.20		
	24	2.20	2.30		


Notes:


- 1. Tolerance of Luminous Intensity ±10%
- 2.Tolerance of Dominant Wavelength ±1nm
- 3.Tolerance of Forward Voltage ±0.05V


Everlight Electronics Co., Ltd. http://www.everlight.com Rev. 1 Page: 4 of 10 Device No:SZDSE-191-G04 Prepared date: 29-Dec-2004 Prepared by: Wu xiaowei


Typical Electro-Optical














Label explanation


CAT: Luminous Intensity Rank

HUE: Dom. Wavelength Rank

REF: Forward Voltage Rank



Reel Dimensions



Note: The tolerances unless mentioned is ± 0.1 mm, Unit = mm


Everlight Electronics Co., Ltd. Device No:SZDSE-191-G04

http://www.everlight.com

Rev. 1 Page: 6 of 10


Prepared date: 29-Dec-2004 Prepared by: Wu xiaowei

Carrier Tape Dimensions: Loaded quantity 3000 PCS per reel



Note: The tolerances unless mentioned is ± 0.1 mm, Unit = mm

Moisture Resistant Packaging



Everlight Electronics Co., Ltd. Device No:SZDSE-191-G04 http://www.everlight.com Prepared date: 29-Dec-2004

Prepared by: Wu xiaowei

Page: 7 of 10

Rev. 1



Page: 8 of 10

Reliability Test Items And Conditions

The reliability of products shall be satisfied with items listed below.

Confidence level: 90%

LTPD: 10%

No.	Items	Test Condition	Test Hours/Cycles	Sample Size	Ac/Re
1	Reflow Soldering	Temp. : 260°C±5°C Min. 5sec.	6 Min.	22 PCS.	0/1
2	Temperature Cycle	$H: +100^{\circ}\mathbb{C}$ 15min \int 5 min $L: -40^{\circ}\mathbb{C}$ 15min	300 Cycles	22 PCS.	0/1
3	Thermal Shock	$H: +100^{\circ}\mathbb{C}$ 5min $\int 10 \sec$ $L: -10^{\circ}\mathbb{C}$ 5min	300 Cycles	22 PCS.	0/1
4	High Temperature Storage	Temp. : 100°C	1000 Hrs.	22 PCS.	0/1
5	Low Temperature Storage	Temp. : -40°€	1000 Hrs.	22 PCS.	0/1
6	DC Operating Life	$I_F = 20 \text{ mA}$	1000 Hrs.	22 PCS.	0/1
7	High Temperature / High Humidity	85°C / 85%RH	1000 Hrs.	22 PCS.	0/1

Everlight Electronics Co., Ltd. http://www.everlight.com Rev. 1 Device No:SZDSE-191-G04 Prepared date: 29-Dec-2004 Prepared by: Wu xiaowei

Precautions For Use


1. Over-current-proof

Customer must apply resistors for protection, otherwise slight voltage shift will cause big current change (Burn out will happen).

- 2. Storage
 - 2.1 Do not open moisture proof bag before the products are ready to use.
 - 2.2 Before opening the package, the LEDs should be kept at 30°C or less and 90%RH or less.
 - 2.3 The LEDs should be used within a year.
 - 2.4 After opening the package, the LEDs should be kept at 30°C or less and 70% RH or less.
 - 2.5 The LEDs should be used within 168 hours (7 days) after opening the package.
 - 2.6 If the moisture absorbent material (silica gel) has faded away or the LEDs have exceeded the storage time, baking treatment should be performed using the following conditions.

Baking treatment : $60\pm5^{\circ}$ C for 24 hours.

- 3. Soldering Condition
- 3.1 Pb-free solder temperature profile



- 3.2 Reflow soldering should not be done more than two times.
- 3.3 When soldering, do not put stress on the LEDs during heating.
- 3.4 After soldering, do not warp the circuit board.
- 4. Soldering Iron


Each terminal is to go to the tip of soldering iron temperature less than 280°C for 3 seconds within once in less than the soldering iron capacity 25W. Leave two seconds and more intervals, and do soldering of each terminal. Be careful because the damage of the product is often started at the time of the hand solder.

Everlight Electronics Co., Ltd. http://www.everlight.com Rev. 1 Page: 9 of 10 Device No:SZDSE-191-G04 Prepared date: 29-Dec-2004 Prepared by: Wu xiaowei



5.Repairing

Repair should not be done after the LEDs have been soldered. When repairing is unavoidable, a double-head soldering iron should be used (as below figure). It should be confirmed beforehand whether the characteristics of the LEDs will or will not be damaged by repairing.



EVERLIGHT ELECTRONICS CO., LTD.

Office: No 25, Lane 76, Sec 3, Chung Yang Rd, Tucheng, Taipei 236, Taiwan, R.O.C Tel: 886-2-2267-2000, 2267-9936

Fax: 886-2267-6244, 2267-6189, 2267-6306

http://www.everlight.com

Everlight Electronics Co., Ltd. http://www.everlight.com Rev. 1 Page: 10 of 10 Device No:SZDSE-191-G04 Prepared date: 29-Dec-2004 Prepared by: Wu xiaowei