# **Low Pass Filter**

DC<sup>(1)</sup> to 850 MHz 50Q

#### **Maximum Ratings**


Operating Temperature	-55°C to 100°C
Storage Temperature	-55°C to 100°C
RF Power Input*	10W max at 25°C


<sup>\*</sup> Passband rating, derate linearly to 3.5-W at 100°C ambient Permanent damage may occur if any of these limits are exceeded.

#### Pin Connections

RF IN	1
RF OUT	3
GROUND	2,4

#### Outline Drawing






Suggested Layout, Tolerance to be within ±.002

#### Outline Dimensions (inch)

	G	F	E	D	С	В	Α
	.169	.009	.032	.020	.037	.063	.126
	4.29	0.23	0.81	0.51	0.94	1.60	3.20
wt	Р	N	M	L	K	J	Н
grams	.071	.012	.087	.024	.122	.024	.087
.020	1.80	0.30	2.21	0.61	3.10	0.61	2.21

#### Demo Board MCL P/N: TB-270 Suggested PCB Layout (PL-137)



COPLANAR WAVEGUIDE PARAMETERS ARE SHOWN FOR ROGERS RO4350B WITH THICKNESS .020" ± .0015". COPPER: 1/2 OZ. EACH SIDE. FOR OTHER MATERIALS TRACE WIDTH & GAP MAY NEED TO BE MODIFIED.

BOTTOM SIDE OF THE PCB IS CONTINUOUS GROUND PLANE.

DENOTES PCB COPPER LAYOUT WITH SMOBC
(SOLDER MASK OVER BARE COPPER)

DENOTES COPPER LAND PATTERN FREE OF SOLDER MASK

#### **Features**

- excellent power handling, 10W
- small size
- 7 sections
- temperature stable
- LTCC construction
- rejection in stopband, 45-50 dB typ.
- protected by U.S Patent 6,943,646

#### **Applications**

- harmonic rejection
- VHF/UHF transmitters/receivers
- lab use

#### Flectrical Specifications (1,2) at 25°C

## LFCN-900+



Generic photo used for illustration purposes only CASE STYLE: FV1206

+RoHS Compliant

The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications



Liectifical Specifications at 25 C								
Pa	rameter	F#	Frequency (MHz)	Min.	Тур.	Max.	Unit	
Pass Band	Insertion Loss	DC-F1	DC-850	_	_	1.3	dB	ĺ
	Freq. Cut-Off	F2	1075	_	3.0	_	dB	l
	VSWR	DC-F1	DC-850	_	1.2	_	:1	
Stop Band		F3	1275	20	_	_	dB	l
	Rejection Loss	F4-F5	1350-4850	_	30	_	dB	
		F6	5100	_	20	_	dB	١
						I		1

(1) In Applications where DC isolation to ground is required, coupling capacitors are recommended to avoid DC leakage. Alternatively, if DC pass IN-OUT is required, Mini-Circuits' "D" suffix version of this model will support DC IN-OUT, and provide>100 MOhm isolation to ground. (2) Measured on Mini-Circuits Characterization Test Board TB-270.

### Typical Frequency Response 20 ATTENUATION DC: F1 F2 F3 F4 **FREQUENCY**


#### **Electrical Schematic**



Typical Performance Data at 25°C

	.,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,						
Frequency (MHz)	Insertion Loss (dB)	VSWR (:1)					
50.00	0.10	1.05					
500.00	0.38	1.14					
840.00	0.81	1.14					
1075.00	3.36	1.88					
1275.00	28.73	18.50					
1300.00	29.98	20.22					
1350.00	31.63	23.18					
2600.00	51.39	52.65					
2860.00	48.32	51.10					
4840.00	28.59	32.79					
5000.00	26.32	30.49					
5200.00	21.44	25.94					
6500.00	21.81	20.22					
7000.00	20.93	21.73					
8000.00	20.09	22.29					





A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms\_isp

### **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Mini-Circuits: