## **ON Semiconductor**

### Is Now



To learn more about onsemi™, please visit our website at www.onsemi.com

onsemi and ONSEMI. and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. onsemi reserves the right to make changes at any time to any products or information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/ or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use onsemi products for any such unintended or unauthorized application,

## NTS260SF

# Very Low Forward Voltage Trench-based Schottky Rectifier

#### **Features**

- Fine Lithography Trench-based Schottky Technology for Very Low Forward Voltage and Low Leakage
- Fast Switching with Exceptional Temperature Stability
- Low Power Loss and Lower Operating Temperature
- Higher Efficiency for Achieving Regulatory Compliance
- Low Thermal Resistance
- High Surge Capability
- NRV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC-Q101 Qualified and PPAP Capable
- These Devices are Pb–Free, Halogen Free/BFR Free and are RoHS Compliant

#### **Mechanical Characteristics:**

- Case: Molded Epoxy
- Epoxy Meets UL 94 V-0 @ 0.125 in
- Weight: 11.7 mg (Approximately)
- Lead and Mounting Surface Temperature for Soldering Purposes: 260°C Maximum for 10 Seconds
- MSL 1

#### **Typical Applications**

 Switching Power Supplies including Compact Adapters and Flat Panel Display

1

- High Frequency and DC–DC Converters
- Freewheeling and OR-ing diodes
- Reverse Battery Protection
- Instrumentation



#### ON Semiconductor®

www.onsemi.com

# TRENCH SCHOTTKY RECTIFIER 2.0 AMPERES 60 VOLTS



SOD-123FL CASE 498

#### **MARKING DIAGRAM**



AAD = Specific Device Code

M = Date Code ■ Pb–Free Package

(Note: Microdot may be in either location)

#### **ORDERING INFORMATION**

| Device      | Package              | Shipping <sup>†</sup> |
|-------------|----------------------|-----------------------|
| NTS260SFT1G | SOD-123<br>(Pb-Free) | 3000/Tape & Reel      |
| NTS260SFT3G | SOD-123<br>(Pb-Free) | 10000/Tape & Reel     |

<sup>†</sup>For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specification Brochure, BRD8011/D.

#### NTS260SF

#### **MAXIMUM RATINGS**

| Rating  | Symbol   | Value       | Unit |
|---|--|-------------|------|
| Peak Repetitive Reverse Voltage<br>Working Peak Reverse Voltage<br>DC Blocking Voltage                      | V <sub>RRM</sub><br>V <sub>RWM</sub><br>V <sub>R</sub> | 60          | V    |
| Average Rectified Forward Current (T <sub>L</sub> = 103°C)  | Io   | 2.0         | Α    |
| Peak Repetitive Forward Current (Square Wave, 20 kHz, T <sub>L</sub> = 112°C)                               | I <sub>FRM</sub>                                       | 4.0         | Α    |
| Non-Repetitive Peak Surge Current<br>(Surge Applied at Rated Load Conditions Halfwave, Single Phase, 60 Hz) | I <sub>FSM</sub>                                       | 25          | А    |
| Storage and Operating Junction Temperature Range (Note 1)   | T <sub>stg</sub> , T <sub>J</sub>                      | -65 to +150 | °C   |

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

#### THERMAL CHARACTERISTICS

| Characteristic                                   | Symbol          | Value | Unit |
|--|-----------------|-------|------|
| Thermal Resistance, Junction-to-Lead (Note 2)    | $\Psi_{JCL}$    | 24.4  | °C/W |
| Thermal Resistance, Junction-to-Ambient (Note 2) | $R_{\theta JA}$ | 85    | °C/W |
| Thermal Resistance, Junction-to-Ambient (Note 3) | $R_{	heta JA}$  | 330   | °C/W |

#### **ELECTRICAL CHARACTERISTICS**

| Characteristic  | Symbol         | Value                        | Unit     |
|---|----------------|------------------------------|----------|
| Maximum Instantaneous Forward Voltage (Note 4) $ \begin{aligned} (I_F = 1.0 \text{ A, } T_J = 25^{\circ}\text{C}) \\ (I_F = 2.0 \text{ A, } T_J = 25^{\circ}\text{C}) \\ (I_F = 1.0 \text{ A, } T_J = 125^{\circ}\text{C}) \\ (I_F = 2.0 \text{ A, } T_J = 125^{\circ}\text{C}) \end{aligned} $ | V <sub>F</sub> | 0.55<br>0.65<br>0.48<br>0.57 | V        |
| Maximum Instantaneous Reverse Current (Note 4) (Rated dc Voltage, $T_J = 25^{\circ}C$ ) (Rated dc Voltage, $T_J = 125^{\circ}C$ )   | I <sub>R</sub> | 50<br>5                      | μA<br>mA |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.


2. Mounted with 700 mm² copper pad size (Approximately 1 in²) 1 oz FR4 Board.


- 3. Mounted with pad size approximately 20 mm² copper, 1 oz FR4 Board. 4. Pulse Test: Pulse Width  $\leq$  380  $\mu$ s, Duty Cycle  $\leq$  2.0%.

<sup>1.</sup> The heat generated must be less than the thermal conductivity from Junction–to–Ambient:  $dP_D/dT_J < 1/R_{\theta JA}$ .

#### NTS260SF

#### TYPICAL CHARACTERISTICS





**Figure 5. Typical Junction Capacitance** 






Figure 6. Current Derating





SOD-123FL **CASE 498** ISSUE D

**DATE 10 MAY 2013** 










# RECOMMENDED SOLDERING FOOTPRINT\*



**DIMENSIONS: MILLIMETERS** 

#### NOTES:

- ES:
  DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
  CONTROLLING DIMENSION: MILLIMETER.
  DIMENSIONS A AND B DO NOT INCLUDE MOLD FLASH.
  DIMENSIONS D AND J ARE TO BE MEASURED ON FLAT SECTION
  OF THE LEAD: BETWEEN 0.10 AND 0.25 MM FROM THE LEAD TIP.

|     | MILLIMETERS |      |      | INCHES |       |       |
|-----|-------------|------|------|--------|-------|-------|
| DIM | MIN         | NOM  | MAX  | MIN    | NOM   | MAX   |
| Α   | 0.90        | 0.95 | 0.98 | 0.035  | 0.037 | 0.039 |
| A1  | 0.00        | 0.05 | 0.10 | 0.000  | 0.002 | 0.004 |
| b   | 0.70        | 0.90 | 1.10 | 0.028  | 0.035 | 0.043 |
| С   | 0.10        | 0.15 | 0.20 | 0.004  | 0.006 | 0.008 |
| D   | 1.50        | 1.65 | 1.80 | 0.059  | 0.065 | 0.071 |
| E   | 2.50        | 2.70 | 2.90 | 0.098  | 0.106 | 0.114 |
| L   | 0.55        | 0.75 | 0.95 | 0.022  | 0.030 | 0.037 |
| HE  | 3.40        | 3.60 | 3.80 | 0.134  | 0.142 | 0.150 |
| θ   | 0°          | -    | 8°   | 0°     | -     | 8°    |

#### **GENERIC MARKING DIAGRAM\***



XXX = Specific Device Code

= Date Code

= Pb-Free Package

(Note: Microdot may be in either location)

\*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot " ■", may or may not be present.

| DOCUMENT NUMBER: | 98AON11184D | Electronic versions are uncontrolled except when accessed directly from the Document Repositor Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red. |             |
|------------------|-------------|--|-------------|
| DESCRIPTION:     | SOD-123FL   |  | PAGE 1 OF 1 |

ON Semiconductor and unare trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. ON Semiconductor does not convey any license under its patent rights nor the rights of others.

<sup>\*</sup>For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

ON Semiconductor and the are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor and see no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and

#### **PUBLICATION ORDERING INFORMATION**

LITERATURE FULFILLMENT:
Email Requests to: orderlit@onsemi.com

ON Semiconductor Website: www.onsemi.com

TECHNICAL SUPPORT North American Technical Support: Voice Mail: 1 800-282-9855 Toll Free USA/Canada Phone: 011 421 33 790 2910

Europe, Middle East and Africa Technical Support:

Phone: 00421 33 790 2910

For additional information, please contact your local Sales Representative