

### **SCM Series**

SMD Common Mode Choke Size 9266

### **FEATURES**


- Chip common mode filter for large current applications.
- Low profile design makes it optimal for surface mounting.
- Operating temperature -40~+125 °C





### **APPLICATIONS**


- Power line noise countermeasure for various electronic equipment
- Noise countermeasure for adapter lines and battery lines or larger electronic equipment such as note PCs and word processors

## Dimensions: [mm]










Land Pattern: [mm]

## Schematic:




# Construction: Wire Type:





## Irms Derating Characteristics:



Current derating at ambient temperature of >85 °C 环境温度高于85摄氏度时电流降额使用曲线



# **Electrical Properties:**

规格型号	单组电感量	公差	峰值共模阻抗	额定电流	单组直流电阻	绝缘电压	额定电压
Part No.	L(µH)	%	Zmax (Ω)	I <sub>R</sub> (mA)	max (Ω)	Vac	Vrms
SCM9266-220Y	22 x2	+50/-30	1600 @105MHz	700	0.14	500	80
SCM9266-470Y	47 x2	+50/-30	3300 @47MHz	500	0.25	500	80
SCM9266-510Y	51 x2	+50/-30	3300 @45MHz	500	0.25	500	80
SCM9266-101Y	100 x2	+50/-30	5000 @21MHz	500	0.28	500	80
SCM9266-200Y	20 x3	+50/-30	1250 @105MHz	500	0.16	500	80
SCM9266-980Y	98 x3	+50/-30	4980 @21MHz	450	0.45	500	80

# Typical Electrical Characteristics:

## Typical Impedance Characteristics:

