

# HESD5Z24

# **Transient Voltage Suppressors**

#### DESCRIPTION

The HESD5Z24 is designed to protect voltage sensitive components from ESD and transient voltage events. Excellent clamping capability, low leakage, and fast response time, make these parts ideal for ESD protection on designs where board space is at a premium. Because of its small size, it is suited for use in cellular phones, portable devices, digital cameras, power supplies and many other portable applications.

#### ORDERING INFORMATION


Device: HESD5Z24Package: SOD-523

♦ Marking: 5S

♦ Material: Halogen free and RoHS compliant

♦ Packing: Tape & Reel♦ Quantity per reel: 3,000pcs

#### PIN CONFIGURATION



#### **FEATURES**

- ♦IEC61000-4-2 Level 4 ESD Protection
- ♦ Protects one directional I/O line
- ♦Low clamping voltage
- ♦ Working voltages : 24V
- ♦Low leakage current

## **MACHANICAL DATA**

♦SOD-523 package

♦ Flammability Rating: UL 94V-0

♦Packaging: Tape and Reel

♦ High temperature soldering guaranteed: 260°C/10s

♦ Reel size: 7 inch

#### **APPLICATIONS**

- ♦ Microprocessor based equipment
- ♦Personal Digital Assistants (PDA's)
- ♦Notebooks, Desktops, and Servers
- ♦Portable Instrumentation
- ♦Peripherals
- **♦Pagers**

#### **PACKAGE OUTLINE**



#### **ABSOLUTE MAXIMUM RATING**

Symbol	Parameter	Value	Unit	
V <sub>ESD</sub>	ESD per IEC 61000-4-2 (Air)	±15	kV	
	ESD per IEC 61000-4-2 (Contact)	±8		
P <sub>D</sub>	Total Power Dissipation on FR-5 Board (Note 1) @ Ta=25°C	150	mW	
T <sub>OPT</sub>	Operating Temperature	-55~125	°C	
T <sub>STG</sub>	Storage Temperature	-55~150	°C	

These ratings are limiting values above which the serviceability of the diode may be impaired. Note 1: FR-5=1.0x0.75x0.62 in.




# HESD5Z24


# **Transient Voltage Suppressors**


# **ELECTRICAL CHARACTERISTICS (Tamb=25°C)**


Symbol	Parameter	Test Condition	Min	Тур	Max	Units
V <sub>RWM</sub>	Reverse Working Voltage				24	V
$V_{BR}$	Reverse Breakdown Voltage	I <sub>T</sub> = 1mA	26			V
I <sub>R</sub>	Reverse Leakage Current	V <sub>RWM</sub> = 24V			1	μA
Vc	Clamping Voltage	$I_{PP} = 1A, t_p = 8/20 \mu s$			35	V
CJ	Junction Capacitance	$V_R = 0V$ , $f = 1MHz$			50	pF

## **ELECTRICAL CHARACTERISTICS CURVE**











# HESD5Z24

# **Transient Voltage Suppressors**

# **SOD-523 PACKAGE OUTLINE DIMENSIONS**

