## **NUF2114**

# 2 Line Audio EMI Filter with ESD Protection

This device is a 2 line audio EMI filter array designed for speaker applications. It offers greater than -30 dB attenuation at frequencies from 900 MHz to 3.0 GHz. This device also offers ESD protection-clamping transients from static discharges and ESD protection is provided across all capacitors.

#### **Features**

- Provides EMI Filtering and ESD Protection
- Integration of 10 Discretes
- Compliance with IEC61000-4-2 (Level 4) 30 kV (Contact)
- DFN8, 2x2 mm Package
- Moisture Sensitivity Level 1
- ESD Ratings: Machine Model = C Human Body Model = 3B
- Matching Series Impedances for Speaker Applications
- This is a Pb-Free Device


#### **Applications**

- Wireless Phones
- MP3s
- PDAs
- Digital Cameras
- Portable DVDs



## ON Semiconductor®

http://onsemi.com



(Top View)

#### MARKING DIAGRAM



DFN8 CASE 506AA




 $\begin{array}{ll} U4 & = \text{Specific Device Code} \\ \overline{M} & = \text{Date Code} \end{array}$ 

= Pb-Free Package

(Note: Microdot may be in either location)

#### **PIN CONNECTIONS**



(Bottom View)

#### **ORDERING INFORMATION**

Device	Package	Shipping <sup>†</sup>
NUF2114MNT1G	DFN8 (Pb-Free)	3000 / Tape & Reel

<sup>†</sup>For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specification Brochure, BRD8011/D.

<sup>\*</sup>For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

#### NUF2114

#### **MAXIMUM RATINGS**

Parameter		Symbol	Value	Unit
ESD Discharge IEC61000-4-2	Contact Discharge	$V_{PP}$	30	kV
Steady-State Power per Resistor @ 25°C		$P_{R}$	180	mW
Steady-State Power per Package @ 25°C		P <sub>T</sub>	360	mW
Operating Temperature Range		T <sub>OP</sub>	-40 to 85	°C
Storage Temperature Range		T <sub>stg</sub>	-55 to 150	°C
Maximum Lead Temperature for Soldering Purposes	(1.8 in from case for 10 s)	TL	260	°C

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

## **ELECTRICAL CHARACTERISTICS** (T<sub>J</sub> = 25°C unless otherwise noted)


Parameter	Test Conditions	Symbol	Min	Тур	Max	Unit
Maximum Reverse Working Voltage		$V_{RWM}$	-	-	12	V
Breakdown Voltage	I <sub>R</sub> = 1.0 mA	$V_{BR}$	13.7	15.7	17.7	V
Leakage Current	V <sub>RWM</sub> = 12 V	I <sub>R</sub>	-	-	0.1	μΑ
Resistance	I <sub>F</sub> = 40 mA	R	8.1	9.0	9.9	Ω
Capacitance per Diode (Notes 1, 3)		C <sub>d</sub>	51	60	66	pF
Cut-Off Frequency (Note 2)	Above this frequency, appreciable attenuation occurs	f <sub>3dB</sub>		50		MHz

- 1. Measured at 25°C,  $V_R = 0$  V, f = 1.0 MHz. 2.  $50~\Omega$  source and  $50~\Omega$  load termination. 3. Total line capacitance is 2 times the diode capacitance ( $C_d$ ).

### NUF2114

### **TYPICAL PERFORMANCE CURVES**


(T<sub>A</sub> = 25°C unless otherwise specified)



0 -10 -20 -30 -30 -50 -60 -70 -80 1.0E+6 10E+6 100E+6 1.0E+9 10E+9 FREQUENCY (Hz)

Figure 1. Insertion Loss Characteristics

Figure 2. Analog Cross-Talk






Figure 3. Typical Resistance over Temperature

Figure 4. Typical Line Capacitance vs. Reverse Bias Voltage

**TOP VIEW** 

←D2 →

DETAIL B






0.10


0.10 С


**DETAIL A** 


#### DFN8 2x2, 0.5P CASE 506AA **ISSUE F**

**DATE 04 MAY 2016** 










#### NOTES

- DIMENSIONING AND TOLERANCING PER
- ASME Y14.5M, 1994 . CONTROLLING DIMENSION: MILLIMETERS. DIMENSION & APPLIES TO PLATED TERMINAL AND IS MEASURED BETWEEN 0.15 AND 0.20 MM FROM TERMINAL TIP. COPLANARITY APPLIES TO THE EXPOSED
- PAD AS WELL AS THE TERMINALS.

	MILLIMETERS			
DIM	MIN	MAX		
Α	0.80	1.00		
A1	0.00	0.05		
А3	0.20 REF			
b	0.20	0.30		
D	2.00	2.00 BSC		
D2	1.10	1.30		
Е	2.00	2.00 BSC		
E2	0.70	0.90		
Ф	0.50 BSC			
Κ	0.30 REF			
Ĺ	0.25	0.35		
L1		0.10		

#### **RECOMMENDED SOLDERING FOOTPRINT\***



DIMENSIONS: MILLIMETERS

0.10 CAB е С 0.05 NOTE 3 **BOTTOM VIEW** 

#### **GENERIC MARKING DIAGRAM\***



XX = Specific Device Code

= Date Code

= Pb-Free Device

\*For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

DOCUMENT NUMBER:	98AON18658D	Electronic versions are uncontrolled except when accessed directly from the Document Repositor Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.	
DESCRIPTION:	DFN8. 2.0X2.0. 0.5MM PITO	CH	PAGE 1 OF 1

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

<sup>\*</sup>This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "•", may or may not be present. Some products may not follow the Generic Marking.

onsemi, ONSEMI, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. Onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer pu

#### **PUBLICATION ORDERING INFORMATION**

LITERATURE FULFILLMENT: Email Requests to: orderlit@onsemi.com

onsemi Website: www.onsemi.com

TECHNICAL SUPPORT North American Technical Support: Voice Mail: 1 800-282-9855 Toll Free USA/Canada Phone: 011 421 33 790 2910

Europe, Middle East and Africa Technical Support:

Phone: 00421 33 790 2910

For additional information, please contact your local Sales Representative