

SCES554D - MARCH 2004 - REVISED DECEMBER 2013

# **Dual 2-Input NAND Gate With Open-Drain Outputs**

Check for Samples: SN74LVC2G38

#### **FEATURES**

- Available in the Texas Instruments NanoFree<sup>™</sup> Package
- Supports 5-V V<sub>CC</sub> Operation
- Inputs Accept Voltages to 5.5 V •
- Max t<sub>pd</sub> of 4 ns at 3.3 V
- Low Power Consumption, 10-µA Max I<sub>CC</sub>
- ±24-mA Output Drive at 3.3 V
- Typical V<sub>OLP</sub> (Output Ground Bounce) <0.8 V at  $V_{CC} = 3.3 V, T_A = 25^{\circ}C$
- Typical V<sub>OHV</sub> (Output V<sub>OH</sub> Undershoot) >2 V at V<sub>CC</sub> = 3.3 V, T<sub>A</sub> = 25°C
- Ioff Supports Live insertion, Partial-Power-**Down Mode Operation and Back Drive** Protection
- Latch-Up Performance Exceeds 100 mA Per JESD 78, Class II
- ESD Protection Exceeds JESD 22
  - 2000-V Human-Body Model (A114-A)
  - 200-V Machine Model (A115-A)
  - 1000-V Charged-Device Model (C101)

See mechanical drawings for dimensions.

#### DESCRIPTION

The SN74LVC2G38 is designed for 1.65-V to 5.5-V  $V_{CC}$  operation.

This device is a dual two-input NAND buffer gate with open-drain outputs. It performs the Boolean function  $Y = \overline{A \bullet B}$  or  $Y = \overline{A} + \overline{B}$  in positive logic.

NanoFree<sup>™</sup> package technology is a major breakthrough in IC packaging concepts, using the die as the package.

This device is fully specified for partial-power-down applications using  $I_{\text{off}}$ . The  $I_{\text{off}}$  circuitry disables the outputs, preventing damaging current backflow through the device when it is powered down.

DCT PACKAGE (TOP VIEW)				DCU PACK (TOP VIE	
1A 🗔	1	8 🗔 V <sub>C</sub> (	C 1A []	1	8 ∐ V <sub>CC</sub>
1B 🗔	2	7 🗖 1Y	1B	2 3	7
2Y 🗔	3	6 🗔 2B	GND 🗔	4	5 ∐ 2A
GND 🖂	4	5 🗔 2A			

YZP PACKA	GE
(BOTTOM VI	EW)

GND	0450	2A
2Y	O36O	2B
1B	0270	1Y
1A	0180	V <sub>CC</sub>

 $\overline{M}$ 

Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet. NanoFree is a trademark of Texas Instruments.

### SN74LVC2G38

SCES554D-MARCH 2004-REVISED DECEMBER 2013

TEXAS INSTRUMENTS


www.ti.com



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

Function Table (Each Gate)						
INP	UTS	OUTPUT				
Α	В	Y				
L	L	Н				
L	Н	Н				
н	L	н				
н	Н	L				

#### Logic Diagram (Positive Logic)



#### Absolute Maximum Ratings<sup>(1)</sup>

over operating free-air temperature range (unless otherwise noted)

			MIN	MAX	UNIT
V <sub>CC</sub>	Supply voltage range		-0.5	6.5	V
VI	Input voltage range <sup>(2)</sup>	Input voltage range <sup>(2)</sup>			V
Vo	Voltage range applied to any output in the high-impedance or power-off state <sup>(2)</sup>			6.5	V
Vo	Voltage range applied to any output in the high	Voltage range applied to any output in the high or low state <sup>(2) (3)</sup>		$V_{CC} + 0.5$	V
I <sub>IK</sub>	Input clamp current	V <sub>1</sub> < 0		-50	mA
I <sub>OK</sub>	Output clamp current	V <sub>O</sub> < 0		-50	mA
I <sub>O</sub>	Continuous output current			±50	mA
	Continuous current through $V_{CC}$ or GND			±100	mA
		DCT package		220	
$\theta_{JA}$	Package thermal impedance <sup>(4)</sup>	DCU package		227	°C/W
		YZP package		102	
T <sub>stg</sub>	Storage temperature range		-65	150	°C

(1) Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

(2) The input and output negative-voltage ratings may be exceeded if the input and output current ratings are observed.

(3) The value of  $V_{CC}$  is provided in the recommended operating conditions table.

(4) The package thermal impedance is calculated in accordance with JESD 51-7.



### Recommended Operating Conditions<sup>(1)</sup>

			MIN	MAX	UNIT	
V	Supply voltage	Operating	1.65	5.5	V	
V <sub>CC</sub>	Supply voltage	Data retention only	1.5		v	
		$V_{CC} = 1.65 \text{ V to } 1.95 \text{ V}$	0.65 × V <sub>CC</sub>			
V	Lish loval input valtage	$V_{CC}$ = 2.3 V to 2.7 V	1.7		V	
V <sub>IH</sub>	High-level input voltage	$V_{CC} = 3 V \text{ to } 3.6 V$	2		v	
		$V_{CC}$ = 4.5 V to 5.5 V	$0.7 \times V_{CC}$			
		$V_{CC} = 1.65 \text{ V} \text{ to } 1.95 \text{ V}$		$0.35 \times V_{CC}$		
V.	Low-level input voltage $V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$ $V_{CC} = 3 \text{ V to } 3.6 \text{ V}$		0.7	v		
V <sub>IL</sub>		$V_{CC} = 3 V \text{ to } 3.6 V$		0.8	v	
		$V_{CC}$ = 4.5 V to 5.5 V		$0.3 \times V_{CC}$		
VI	Input voltage			5.5	V	
Vo	Output voltage		0	V <sub>CC</sub>	V	
		V <sub>CC</sub> = 1.65 V		4		
		$V_{CC} = 2.3 V$		8		
I <sub>OL</sub>	Low-level output current	$V_{\rm GC} = 3 V$		16	mA	
		$v_{CC} = 3 v$		24		
		$V_{CC} = 4.5 V$		32		
		$V_{CC}$ = 1.8 V ± 0.15 V, 2.5 V ± 0.2 V		20		
Δt/Δv	Input transition rise or fall rate	$V_{CC} = 3.3 \text{ V} \pm 0.3 \text{ V}$		10	ns/V	
		$V_{CC} = 5 V \pm 0.5 V$		5		
T <sub>A</sub>	Operating free-air temperature		-40	125	°C	

(1) All unused inputs of the device must be held at V<sub>CC</sub> or GND to ensure proper device operation. Refer to the TI application report, Implications of Slow or Floating CMOS Inputs, literature number SCBA004.

#### **Electrical Characteristics**

over recommended operating free-air temperature range (unless otherwise noted)

PARAMETER		TEST CONDITIONS		–40°C to 85°C	-40°C to 125°C	UNIT	
P	ARAINETER	TEST CONDITIONS	V <sub>cc</sub>	MIN TYP <sup>(1)</sup> MAX	MIN TYP <sup>(1)</sup> MAX		
		I <sub>OL</sub> = 100 μA	1.65 V to 5.5 V	0.1	0.1		
		I <sub>OL</sub> = 4 mA	1.65 V	0.45	0.45		
V		I <sub>OL</sub> = 8 mA	2.3 V	0.3	0.3	v	
V <sub>OL</sub>		I <sub>OL</sub> = 16 mA	3 V	0.4	0.4	v	
		I <sub>OL</sub> = 24 mA	3 V	0.55	0.55		
		I <sub>OL</sub> = 32 mA	4.5 V	0.55	0.55		
I <sub>I</sub>	A or B inputs	V <sub>I</sub> = 5.5 V or GND	0 to 5.5 V	±1	±10	μA	
I <sub>off</sub>		$V_{I} \text{ or } V_{O} = 5.5 \text{ V}$	0	±10	±10	μA	
I <sub>CC</sub>		$V_{I} = 5.5 \text{ V or GND}, I_{O} = 0$	1.65 V to 5.5 V	10	10	μA	
ΔI <sub>CC</sub>		One input at $V_{CC}$ – 0.6 V, Other inputs at $V_{CC}$ or GND	3 V to 5.5 V	3 V to 5.5 V 500		μA	
Ci		V <sub>I</sub> = V <sub>CC</sub> or GND	3.3 V	4		pF	
C <sub>o</sub>		$V_{O} = V_{CC}$ or GND	3.3 V	4.5		pF	

(1) All typical values are at  $V_{CC} = 3.3$  V,  $T_A = 25^{\circ}C$ .

### SN74LVC2G38

SCES554D-MARCH 2004-REVISED DECEMBER 2013



www.ti.com

#### **Switching Characteristics**

over recommended operating free-air temperature range, C<sub>L</sub> = 15 pF (unless otherwise noted) (see Figure 1)

						SN74L\ -40°C 1	/C2G38 :o 85°C				
PARAMETER	FROM (INPUT)	TO (OUTPUT)	V <sub>CC</sub> = ± 0.1		V <sub>CC</sub> = ± 0.		V <sub>CC</sub> = ± 0.3		V <sub>CC</sub> = ± 0.5		UNIT
			MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX	
t <sub>pd</sub>	A or B	Y	2.5	8.5	1.5	5.2	1.3	4	0.9	3	ns

#### **Switching Characteristics**

over recommended operating free-air temperature range,  $C_L = 30 \text{ pF}$  or 50 pF (unless otherwise noted) (see Figure 2)

							/C2G38 :o 85°C				UNIT
PARAMETER	FROM (INPUT)	TO (OUTPUT)	V <sub>cc</sub> = ± 0.1		V <sub>CC</sub> = ± 0.		V <sub>CC</sub> = ± 0.3		V <sub>CC</sub> = ± 0.		UNIT
			MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX	
t <sub>pd</sub>	A or B	Y	2.8	10	1.6	6	1.4	4.5	1	3.9	ns

#### **Switching Characteristics**

over recommended operating free-air temperature range, C<sub>L</sub> = 30 pF or 50 pF (unless otherwise noted) (see Figure 2)

PARAMETER							/C2G38 o 125°C				
	FROM (INPUT)	TO (OUTPUT)	V <sub>CC</sub> = ± 0.1		V <sub>CC</sub> = ± 0.		V <sub>CC</sub> = ± 0.3		V <sub>cc</sub> = ± 0.		UNIT
			MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX	
t <sub>pd</sub>	A or B	Y	2.6	10.8	1.6	6.7	1.4	5.1	1	4.3	ns


#### **Operating Characteristics**

 $T_A = 25^{\circ}C$ 

	PARAMETER	TEST CONDITIONS	V <sub>CC</sub> = 1.8 V	$V_{CC}$ = 2.5 V	V <sub>CC</sub> = 3.3 V	$V_{CC} = 5 V$	UNIT
	FARAMETER	TEST CONDITIONS	TYP	TYP	TYP	TYP	UNIT
$C_{\text{pd}}$	Power dissipation capacitance	f = 10 MHz	6	7	7	9	pF




#### Parameter Measurement Information (Open Drain)



- B. Waveform 1 is for an output with internal conditions such that the output is low, except when disabled by the output control. Waveform 2 is for an output with internal conditions such that the output is high, except when disabled by the output control.
   C. All input pulses are supplied by generators have the following characteristics: PRR ≤ 10 MHz, Z<sub>0</sub> = 50 Ω.
- C. All input pulses are supplied by generators have the following characteristics: PRR  $\leq$  10 MHz,  $Z_0 = 50$
- D. The outputs are measured one at a time, with one transition per measurement.
- E. Because this device has open-drain outputs,  $t_{_{PLZ}}$  and  $t_{_{PZL}}$  are the same as  $t_{_{PD}}$
- F.  $t_{_{PZL}}$  is measured at V\_M.
- G.  $t_{_{PLZ}}$  is measured at  $V_{_{OL}}$  +  $V_{_{\Delta}}$
- H. All parameters and waveforms are not applicable to all devices.

#### Figure 1. Load Circuit and Voltage Waveforms

#### SN74LVC2G38 SCES554D – MARCH 2004 – REVISED DECEMBER 2013



B. Waveform 1 is for an output with internal conditions such that the output is low, except when disabled by the output control. Waveform 2 is for an output with internal conditions such that the output is high, except when disabled by the output control.

- C. All input pulses are supplied by generators have the following characteristics: PRR  $\leq$  10 MHz, Z<sub>o</sub> = 50  $\Omega$ .
- D. The outputs are measured one at a time, with one transition per measurement.
- E. Because this device has open-drain outputs,  $t_{\mbox{\tiny PLZ}}$  and  $t_{\mbox{\tiny PZL}}$  are the same as  $t_{\mbox{\tiny PD}}$
- F.  $t_{PZL}$  is measured at V<sub>M</sub>.
- G.  $t_{PLZ}$  is measured at  $V_{OL} + V_{\Delta}$ .
- H. All parameters and waveforms are not applicable to all devices.

#### Figure 2. Load Circuit and Voltage Waveforms

www.ti.com



#### **REVISION HISTORY**

Cł	Changes from Revision C (Feburary 2007) to Revision D P					
•	Updated document to new TI data sheet format.	. 1				
•	Added ESD warning.	. 2				
•	Updated operating temperature range.	. 3				



#### PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead finish/ Ball material	MSL Peak Temp	Op Temp (°C)	Device Marking (4/5)	Samples
	(.)		Ū			(=)	(6)	(0)		()	
SN74LVC2G38DCTR	ACTIVE	SM8	DCT	8	3000	RoHS & Green	NIPDAU	Level-1-260C-UNLIM	-40 to 125	C38 (R, Z)	Samples
SN74LVC2G38DCUR	ACTIVE	VSSOP	DCU	8	3000	RoHS & Green	NIPDAU   SN	Level-1-260C-UNLIM	-40 to 125	(C38J, C38Q, C38R)	Samples
SN74LVC2G38DCUT	ACTIVE	VSSOP	DCU	8	250	RoHS & Green	NIPDAU   SN	Level-1-260C-UNLIM	-40 to 125	(C38J, C38Q, C38R)	Samples
SN74LVC2G38YZPR	ACTIVE	DSBGA	YZP	8	3000	RoHS & Green	SNAGCU	Level-1-260C-UNLIM	-40 to 85	D7N	Samples

<sup>(1)</sup> The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

**LIFEBUY:** TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

**PREVIEW**: Device has been announced but is not in production. Samples may or may not be available.

**OBSOLETE:** TI has discontinued the production of the device.

<sup>(2)</sup> RoHS: TI defines "RoHS" to mean semiconductor products that are compliant with the current EU RoHS requirements for all 10 RoHS substances, including the requirement that RoHS substance do not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, "RoHS" products are suitable for use in specified lead-free processes. TI may reference these types of products as "Pb-Free".

**RoHS Exempt:** TI defines "RoHS Exempt" to mean products that contain lead but are compliant with EU RoHS pursuant to a specific EU RoHS exemption.

Green: TI defines "Green" to mean the content of Chlorine (CI) and Bromine (Br) based flame retardants meet JS709B low halogen requirements of <= 1000ppm threshold. Antimony trioxide based flame retardants must also meet the <= 1000ppm threshold requirement.

<sup>(3)</sup> MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

<sup>(4)</sup> There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

<sup>(6)</sup> Lead finish/Ball material - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and



10-Dec-2020

continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

### PACKAGE MATERIALS INFORMATION

Texas Instruments

www.ti.com

#### TAPE AND REEL INFORMATION





#### QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE




*All dimensions are nominal												
Device	Package Type	Package Drawing		SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
SN74LVC2G38DCTR	SM8	DCT	8	3000	180.0	13.0	3.35	4.5	1.55	4.0	12.0	Q3
SN74LVC2G38DCTR	SM8	DCT	8	3000	177.8	12.4	3.45	4.4	1.45	4.0	12.0	Q3
SN74LVC2G38DCUR	VSSOP	DCU	8	3000	178.0	9.0	2.25	3.35	1.05	4.0	8.0	Q3
SN74LVC2G38DCUR	VSSOP	DCU	8	3000	180.0	8.4	2.25	3.35	1.05	4.0	8.0	Q3
SN74LVC2G38DCUR	VSSOP	DCU	8	3000	178.0	9.5	2.25	3.35	1.05	4.0	8.0	Q3
SN74LVC2G38DCUT	VSSOP	DCU	8	250	178.0	9.5	2.25	3.35	1.05	4.0	8.0	Q3
SN74LVC2G38DCUT	VSSOP	DCU	8	250	178.0	9.0	2.25	3.35	1.05	4.0	8.0	Q3
SN74LVC2G38YZPR	DSBGA	YZP	8	3000	178.0	9.2	1.02	2.02	0.63	4.0	8.0	Q1



### PACKAGE MATERIALS INFORMATION

27-May-2021



*All dimensions are nominal							-
Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
SN74LVC2G38DCTR	SM8	DCT	8	3000	182.0	182.0	20.0
SN74LVC2G38DCTR	SM8	DCT	8	3000	183.0	183.0	20.0
SN74LVC2G38DCUR	VSSOP	DCU	8	3000	180.0	180.0	18.0
SN74LVC2G38DCUR	VSSOP	DCU	8	3000	202.0	201.0	28.0
SN74LVC2G38DCUR	VSSOP	DCU	8	3000	202.0	201.0	28.0
SN74LVC2G38DCUT	VSSOP	DCU	8	250	202.0	201.0	28.0
SN74LVC2G38DCUT	VSSOP	DCU	8	250	180.0	180.0	18.0
SN74LVC2G38YZPR	DSBGA	YZP	8	3000	220.0	220.0	35.0

# **DCU0008A**



# **PACKAGE OUTLINE**

### VSSOP - 0.9 mm max height

SMALL OUTLINE PACKAGE



NOTES:

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M. 2. This drawing is subject to change without notice. 3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not
- exceed 0.15 mm per side. 4. Reference JEDEC registration MO-187 variation CA.



## DCU0008A

# **EXAMPLE BOARD LAYOUT**

### VSSOP - 0.9 mm max height

SMALL OUTLINE PACKAGE



NOTES: (continued)

5. Publication IPC-7351 may have alternate designs.

6. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



## DCU0008A

# **EXAMPLE STENCIL DESIGN**

### VSSOP - 0.9 mm max height

SMALL OUTLINE PACKAGE



NOTES: (continued)

8. Board assembly site may have different recommendations for stencil design.



<sup>7.</sup> Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.


# **DCT0008A**



## **PACKAGE OUTLINE**

### SSOP - 1.3 mm max height

SMALL OUTLINE PACKAGE



NOTES:

- 1. All linear dimensions are in millimeters. Dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M. 2. This drawing is subject to change without notice. 3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not
- exceed 0.15 mm per side.
- 4. This dimension does not include interlead flash. Interlead flash shall not exceed 0.25 mm per side.




## **DCT0008A**

# **EXAMPLE BOARD LAYOUT**

### SSOP - 1.3 mm max height

SMALL OUTLINE PACKAGE



NOTES: (continued)

Publication IPC-7351 may have alternate designs.
 Solder mask tolerances between and around signal pads can vary based on board fabrication site.



## **DCT0008A**

# **EXAMPLE STENCIL DESIGN**

### SSOP - 1.3 mm max height

SMALL OUTLINE PACKAGE



NOTES: (continued)

8. Board assembly site may have different recommendations for stencil design.



<sup>7.</sup> Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.

# YZP0008



## **PACKAGE OUTLINE**

### DSBGA - 0.5 mm max height

DIE SIZE BALL GRID ARRAY



#### NOTES:

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
- 2. This drawing is subject to change without notice.



# YZP0008

# **EXAMPLE BOARD LAYOUT**

### DSBGA - 0.5 mm max height

DIE SIZE BALL GRID ARRAY



NOTES: (continued)

3. Final dimensions may vary due to manufacturing tolerance considerations and also routing constraints. For more information, see Texas Instruments literature number SNVA009 (www.ti.com/lit/snva009).



# YZP0008

# **EXAMPLE STENCIL DESIGN**

### DSBGA - 0.5 mm max height

DIE SIZE BALL GRID ARRAY



NOTES: (continued)

4. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release.



#### IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2023, Texas Instruments Incorporated