

RB161QS-40

1.0A Schottky Barrier Rectifiers

Features

- ◆ The plastic package carries Underwriters Laboratory Flammability Classification 94V-0
- ◆ Low forward voltage
- ◆ Low current leakage
- For surface mounted applications in order to optimize board space
- High temperature soldering guaranteed:
 260 C/10 seconds
- ◆ Compliant to RoHS Directive 2011/65/EU

Applications

- ◆ Low current rectification
- Switch mode power supply
- Inverse polarity protection
- ◆ Low power consumption applications

Marking

Type number	Marking code		
RB161QS-40	40		



SMD1006(0402)



Absolute Maximum Ratings (T=25°C, RH=45%-75%, unless otherwise noted)

Parameters	Symbol	Limit	Unit
Reverse Voltage (Repetitive Peak)	V_{RRM}	40	V
Reverse Voltage (RMS)	V _{R(RMS)}	32	V
DC Blocking Voltage	V _R	40	V
Average Rectified Output Current	I _O	1	А
Non-repetitive Peak Forward Surge Current@t=8.3ms	I _{FSM}	7	А
Power Dissipation	P _D	500	mW
Thermal Resistance Junction to Ambient(Typ)	ReJA	120	°C/W
Junction Temperature	TJ	-55 ~ +125	°C
Storage Temperature	T _{STG}	-55 ~ +150	°C


Electrical Characteristics (T=25°C, RH=45%-75%, unless otherwise noted)


Parameters	Symbol	Test conditions Min.		Тур.	Max.	Unit	
Breakdown V oltage	V _{BR}	I _R =1mA 40			V		
Reverse Current	I _R	V _R =40V		10	40	uA	
Forward Voltage	VF	I _F =100mA			0.38		
		I _F =200mA			0.40		
		I _F =500mA			0.49	V	
		I _F =700mA			0.55		
		I _F =1A			0.60		
Total Capacitance	Ст	V _R =0V,f=1MHz		75	120	pF	





1.0A Schottky Barrier Rectifiers

Rating and characteristic curves













1.0A Schottky Barrier Rectifiers

Package Mechanical Data



9,0

0,35



Recommended soldering footprint(mm)

0,35

Symbol	Millimeters			Inches		
	Min.	Тур.	Max.	Min.	Тур.	Max.
А	0.40	0.50	0.55	0.016	0.020	0.022
A1	0.00	0.02	0.05	0.000	0.001	0.002
b	0.45	0.50	0.55	0.018	0.020	0.022
D	0.95	1.00	1.05	0.037	0.039	0.041
е	0.65BSC			5BSC 0.026BSC		
Е	0.55	0.60	0.65	0.022	0.024	0.026
L	0.20	0.25	0.30	0.008	0.010	0.012