SIEMENS

Data sheet

3LD5000-0TL13



SENTRON, Molded case switch 3LD5 UL, Emergency switching-off, 4-pole, certified according to UL489 UL60947-4-1 and IEC60947-3, UL: 30A, SCCR 50kA at 480VAC, Operating power at 480VAC 3-phase: 20hp, IEC: 32A, Operating power at AC-23A at 400V: 15kW, floor mounting with direct handle, red/yellow, incl. terminal covers for the infeed side

Model	Model		
product brand name	SENTRON		
product designation	3LD UL switch disconnector		
design of the product	EMERGENCY-STOP switch		
display version / for switch position indicator manual operation	1 ON - 0 OFF		
design of the actuating element	selector switch		
design of handle	knob-operated mechanism, red/yellow		
type of the driving mechanism / motor drive	No		
General technical data			
number of poles	4		
type of device	fixed mounting		
type of switch	Floor mounting with direct drive		
size of switch disconnector	1		
mechanical service life (switching cycles) / typical	100 000		
electrical endurance (switching cycles)			
• at AC-23 A / at 690 V	6 000		
I2t value / with closed switch / at 690 V / for combination switch + gG fuse / maximum	12 kA2.s		
let-through I2t value / with closed switch / at 440 V / for combination switch + gG fuse / maximum	12 kA2.s		
operating frequency / maximum	50 1/h		
Voltage			
insulation voltage / rated value	690 V		
surge voltage resistance / rated value	6 kV		
Protection class			
protection class IP	IP00		
protection class IP / on the front	IP00		
Dissipation			
power loss [W]			
 for rated value of the current / at AC / in hot operating state / per pole 	4.5 W		
per conductor / typical	5 W		
Current			
operational current			
• at 40 °C / rated value	32 A		
● at 45 °C / rated value	32 A		
• at 50 °C / rated value	32 A		
• at 55 °C / rated value	32 A		
• at AC / rated value	32 A		

• at AC-23 A / at 400 V / rated value	32 A
• at AC-21 / at 690 V / rated value	32 A
 at AC-21 A / at 240 V / rated value 	32 A
at AC-21 A / at 440 V / rated value	32 A
operational current / of upstream fuse / rated value	40 A
let-through current / with closed switch	
 at 440 V / for combination switch + gG fuse / maximum 	6 kA
 at 690 V / for combination switch + gG fuse / maximum permissible 	6 kA
Main circuit	
operating power	
• at AC-23 A / at 240 V / rated value	7.5 kW
• at AC-23 A / at 440 V / rated value	15 kW
• at AC-23 A / at 690 V / rated value	19 kW
• at AC-3 / at 240 V / rated value	7.5 kW
• at AC-3 / at 400 V / rated value	15 kW
• at AC-3 / at 690 V / rated value	15 kW
operational current / rated value	32 A
Auxiliary circuit	
number of CO contacts / for auxiliary contacts	0
number of NC contacts / for auxiliary contacts	0
number of NO contacts / for auxiliary contacts	0
operating voltage / of auxiliary contacts / at AC / maximum	500 V
continuous current / of the auxiliary contact / rated value	10 A
insulation voltage / of the auxiliary switch / rated value	500 V
Suitability	
suitability for use	
main switch	Yes
 switch disconnector 	Yes
EMERGENCY OFF switch	Yes
 safety switch 	Yes
maintenance/repair switch	Yes
Appearance	
color / of the actuating element	red
Product details	
product feature	
can be locked into OFF position	Yes
number of bracket locks / maximum	1
hasp thickness / of the bracket locks / minimum	4 mm
hasp thickness / of the bracket locks / maximum	
	6 mm
product extension / optional	
motor drive	No
motor drivevoltage trigger	
motor drive	No
motor drivevoltage trigger	No
motor drive voltage trigger Short circuit conditional short-circuit current / with line-side fuse	No
motor drive voltage trigger Short circuit conditional short-circuit current / with line-side fuse protection	No No
 motor drive voltage trigger Short circuit conditional short-circuit current / with line-side fuse protection at 440 V / by gG fuse / rated value at 690 V / by gG fuse / rated value 	No No 50 kA
 motor drive voltage trigger Short circuit conditional short-circuit current / with line-side fuse protection at 440 V / by gG fuse / rated value at 690 V / by gG fuse / rated value according UL operational current / at AC / according to UL 489/UL	No No 50 kA
 motor drive voltage trigger Short circuit conditional short-circuit current / with line-side fuse protection at 440 V / by gG fuse / rated value at 690 V / by gG fuse / rated value according UL operational current / at AC / according to UL 489/UL 60947-4-1 / rated value operational current / at AC / according to UL 508/UL 	No No 50 kA 50 kA
 motor drive voltage trigger Short circuit conditional short-circuit current / with line-side fuse protection at 440 V / by gG fuse / rated value at 690 V / by gG fuse / rated value according UL operational current / at AC / according to UL 489/UL 60947-4-1 / rated value	No No 50 kA 50 kA 30 A
 motor drive voltage trigger Short circuit conditional short-circuit current / with line-side fuse protection at 440 V / by gG fuse / rated value at 690 V / by gG fuse / rated value according UL operational current / at AC / according to UL 489/UL 60947-4-1 / rated value operational current / at AC / according to UL 508/UL 60947-4-1 / rated value operational current / at AC / according to UL 508/UL 60947-4-1 / rated value operating voltage / at AC / at 50/60 Hz / according to UL	No No 50 kA 50 kA 50 kA 30 A 30 A
 motor drive voltage trigger Short circuit conditional short-circuit current / with line-side fuse protection at 440 V / by gG fuse / rated value at 690 V / by gG fuse / rated value according UL operational current / at AC / according to UL 489/UL 60947-4-1 / rated value operational current / at AC / according to UL 508/UL 60947-4-1 / rated value operating voltage / at AC / at 50/60 Hz / according to UL 489 / rated value operating voltage / at AC / at 50/60 Hz / according to UL 	No No 50 kA 50 kA 50 kA 30 A 30 A 30 A

to UL 508/UL 60947-4-1 and UL 489	
continuous current / of upstream fuse / according to UL /	30 A
rated value	
type of fuse / according to UL	Class CC, J
Number	
number of connectable NC contacts / for auxiliary contacts / attachable / maximum	1
number of connectable NO contacts / for auxiliary contacts / attachable / maximum	2
number of connectable CO contacts / for auxiliary contacts / attachable / maximum	0
Connections	
AWG number / as coded connectable conductor cross section / solid	
• maximum	6
• minimum	14
AWG number / as coded connectable conductor cross section / solid / according to UL 489	
• minimum	14
• maximum	6
AWG number / as coded connectable conductor cross section / solid / according to CSA C22.2 No. 5-16	
• minimum	12
• maximum	8
type of connectable conductor cross-sections / for copper conductor	
• solid	1x (2,535mm²)
 finely stranded / with core end processing 	1x (2.516 mm²)
stranded	1x (2,535mm²)
type of connectable conductor cross-sections / for auxiliary contacts	
• solid	2x (0.75 2.5 mm²), 1x 4 mm²
 finely stranded / with core end processing 	2x (0.75 1.5 mm ²), 1x 2.5 mm ²
stranded	2x (0.75 2.5 mm²), 1x 4 mm²
type of electrical connection	
for main current circuit for curviliant contacts	box terminal
for auxiliary contacts	connection terminals
Requirements	
design of the fuse link	
 for short-circuit protection of the main circuit / required 	Fuse gG: 40 A
 for short-circuit protection of the auxiliary switch / required 	fuse gL/gG: 10 A
Mechanical Design	
height	96 mm
width	80 mm
depth	92 mm
fastening method	Built-in unit fixed-mounted version
fastening method	
• 4-hole front mounting	No
 front mounting with central attachment 	No
rail mounting	Yes
net weight	350 g
Environmental conditions	
ambient temperature / during operation	
• minimum	-25 °C
• maximum	55 °C
ambient temperature / during storage / minimum	-25 °C
General Product Approval	Declaration of Conformity









UK CA

other

Miscellaneous

Further information

Information- and Downloadcenter (Catalogs, Brochures,...) http://www.siemens.com/lowvoltage/catalogs Industry Mall (Online ordering system) https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3LD5000-0TL13 Service&Support (Manuals, Certificates, Characteristics, FAQs,...) https://support.industry.siemens.com/cs/ww/en/ps/3LD5000-0TL13 Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...) http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3LD5000-0TL13 CAx-Online-Generator http://www.siemens.com/cax Tender specifications http://www.siemens.com/specifications







