



MESSRS: 深圳亚泽科技

**APPROVAL NO** 710-019 2019.04.09 **DATE** 

**ALUMINUM ELECTROLYTIC** 

# **CAPACITOR**

# APPROVAL SHEET

CATALOG TYPE	DL SERIES
CATALOG TIPE	
USER PART NO.	
适 用 机 种	
特记事项	Halogen-Free

QINGDAO SAMYOUNG ELECTRONICS CO.,LTD. MANAGER OF DEVELOPMENT DEPARTMENT

GONG JANG SUG



**USER APPROVAL:** 

**APPROVAL NO.:** 

SamYoung(Korea): 47,SAGIMAKGOL-RO,JUNGWON-GU,SEONGNAM-SI,GYEONGGI-DO,KOREA

SamYoung(China): No.5 CHANGJIANG ROAD, PINGDU-CITY, SHANDONG-PROVINCE, CHINA



# APPROVAL NO:

710-019

# ALUMINUM ELECTROLYTIC CAPACITOR

PAGE:


1 OF 5

2019.04.09 DATE:

Specifications of D	L Series								
Item	Characteristics								
Rated Voltage Range		50 ~ 100VDC							
Operating Temperature Rang		-40~	+85℃						
Capacitance Tolerance		±20%	(M)	(at 20℃, 120Hz)					
Leakage Current	After 5 n	ninutes, I = 0.01CV	or 2mA, v	hichever is smaller					
(at 20°C)	Where, I: Leakage current	(μA), C: Nominal	capacitan	ce(µF), V: Rated voltage(VDC)					
Dissipation Factor(Tanδ)	Refer to the below table								
Temperature Characteristics		Z(-25°C)/Z(20°C)	4						
(Max.Impedance radio )		Z(-40°C)/Z(20°C)	15	(at 120HZ)					
Load Life	The following specifications shall be satisfied when the capacitors are restored to 20°C after the rated voltage applied for 2000 hours at 85°C.  Capacitance change: ≤±20% of the initial value  Tanō ≤200% of the initial specified value  LC ≤The initial specified value  The following specifications shall be satisfied when the capacitors are restored to 20°C after exposing								
Shelf Life	them at 85°C for 1000 hours without voltage applied.  The rated voltage shall be applied to the capacitors for a minimum of 30 mininutes . at least 24 hours and not more than 48 hours before the measurements.  Capacitance change:≤±20% of the initial value  Tanō ≤200% of the Initial specified value  LC ≤The initial specified value								
Charge & Discharge									
Others	Satisfied characteristics KS C IEC 60384-4								

## A. DIMENSIONS OF DL Series

# B. MARKING: <u>BLACK</u> SLEEVE, <u>SILVER</u> INK





PAGE: 2 OF 5

# ALUMINUM ELECTROLYTIC CAPACITOR

**APPROVAL NO:** 

710-019


## **RATINGS OF DL Series**

VDC	VDC VDC													
μF		50		63				80		100				
2200										30×30	0.25	1.20		
	25.4×30	0.20	1.81	25.4×40	0.20	1.96	25.4×50	0.20	1.07	30×60	0.20	2.32		
3300	30×25	0.20	1.86	30×30	0.25	1.75	30×40	0.20	1.08	35×50	0.20	2.32		
							35×35	0.25	1.86	40×40	0.25	2.28		
	25.4×40	0.25	2.09	25.4×50	0.25	2.21	25.4×60	0.25	2.33	35×60	0.25	2.62		
4700	30×30	0.25	2.09	30×40	0.25	2.22	30×50	0.25	2.35	40×50	0.25	2.61		
	22×40	0.30	1.96	35×30	0.30	2.03	35×40	0.30	2.73					
5600				35×30	0.35	2.03								
				30×40	0.30	2.22								
	25.4×50	0.25	2.65	30×50	0.30	2.58	30×60	0.30	2.72	40×60	0.25	3.29		
6800	30×40	0.25	2.67	35×30	0.35	2.10	35×50	0.30	2.72					
	35×35	0.25	2.67	35×40	0.30	2.57	40×40	0.30	2.72					
	30×50	0.35	2.63	30×60	0.35	2.77	7 35×60 0		3.16					
8200	35×40	0.35	2.61	35×50	0.35	2.77	40×50	0.30	3.15					
				40×40	0.35	2.77								
				30×50	0.35	2.73				35×60	0.45	2.70		
10000	30×50	0.35	2.90	35×60	0.35	3.23	40×60	0.35	3.37	35×70	0.45	3.27		
	35×40	0.35	2.88	40×50	0.35	3.22								
	30×60	0.35	3.32	35×60	0.40	3.31	35×60	0.40	3.16					
12000	35×50	0.35	3.34	40×50	0.40	3.30	50×50	0.40	3.50					
	40×40	0.35	3.35											
							35×60	0.45	3.20					
15000	35×60	0.35	3.85	40×60	0.40	3.86	<del>-</del>	Rated Rippl	e Current(Arr	ms/85˚ℂ,120⊦	Hz)			
	40×50	0.35	3.92				Tanδ(Max)							
22000	40×60	0.35	5.00				Case Size 4							

# **ALUMINUM ELECTROLYTIC CAPACITORS**

APPROVAL NO. 710-019

#### **STRUCTURE and MATERIALS**



## **\* LARGE SIZED TYPE CAPACITORS COMPONENT**

PART NAME	MATERIALS	VENDER						
		KYUNG-WON	(KOREA)					
AL RIVET	ALUMINUM 99.9 %	MECTRON/TNS	(KOREA/CHINA					
		NAN TONG CHUANG JIA	(CHINA)					
		KYUNG-WON	(KOREA)					
TERMINAL	SPCC (Pb-FREE)	MECTRON/TNS	(KOREA/CHINA					
IENWINAL	SPCC (FB-FREE)	NAN TONG CHUANG JIA	(CHINA)					
		JIANGYIN JINMA LVYE	(OIIIIA)					
		ISOVOLTA	(AUSTRIA)					
BAKE	RUBBER + PAPER LAMINATE	FINE POLYMER	(KOREA)					
DAKL	COBBER : FAFER LAWINATE	NAN TONG CHUANG JIA	(CHINA)					
		TNS	(CHINA)					
		KISTRON						
AL TAB	ALUMINUM 99.9 % OVER	SAMYOUNG	(KOREA)					
AL TAB	ALGININGIN 99.9 % OVER	NANTONG HUIFENG						
		DONG YANG	(JAPAN)					
		MOODEUNG	(KOREA)					
SLEEVE	P.E.T(Poly Ethlylene Terephthalate Resin)	YUNLIN PLASTIC						
SLLLVL	F.E.T (Foly Ethiylene Telephthalate Keshi)	erephthalate Resin) SHUN PENG PLASTIC						
		SUZHOU QILIAN						
BOTTOM PLATE	P.P(Polypropylene)	SUNG NAM	(KOREA)					
		D.N TECH/DONG NAM	(KOREA)					
		LINAN AOXING						
AL CASE	ALUMINUM 99.5 %	NANTONG XINLIAN/HAI BANG	(CHINA)					
AL OAGE	ALGINITOW 33.3 /	CHUANGJIA ELETROMECHANICAL	- (0111142)					
		NANTONG CHUANGJIA						
		PONTIGGIA	(ITALIA)					
		SAMYOUNG	(KOREA)					
		K.D.K/JCC/MATSUSHITA	(JAPAN)					
		BECROMAL	(ITALY)					
AL FOIL +	FORMED ALUMINUM 99.9 % OVER	SATMA	(FRANCE)					
ALIGIE	TORMED ALGIMINOUS 55.5 /6 GVER	HUAFENG/NANTONG/RAOIO						
		HEC	(CHINA)					
		XINJIANG JOINWORLD						
		LUXON/LITON	(TAIWAN)					
		K.D.K	(JAPAN)					
AL FOIL	ETCHED ALUMINUM 99.8 % OVER	K-JCC	(KOREA)					
	2. C. L.D ALOMINOM 33.0 /00 VER	AFT/INCULCU/SHENGHONG	(CHINA)					
		ELECON/WU JIANG FEILO	(0111147)					
		N.K.K	(JAPAN)					
SEPARATOR	INSULATION PAPER	SPO	(GERMANY)					
		LUNAN PAPER/KAN	(CHINA)					
ADHESIVE TARE	POLY PROPYLENE OR POLY IMIDE FILM	DAEIL/SWECO	(KOREA)					
ADIILOIVE IMPE	OLI FROFILLIAL OR FOLI IIVIIDE FILIVI	NICHIBAN	(JAPAN)					

PAGE: 4 OF 5

### When using aluminum electrolytic capacitors, pay strict attention to the following:

#### 1. Electrolytic capacitors for DC application require polarization.

Confirm the polarity. If used in reversed polarity, the circuit life may be shortened or the capacitor may be damaged. For use on circuits whose polarity is occasionally reversed, or whose polarity is unknown, use bi-polarized capacitors (BP-series). Also, note that the electrolytic capacitor cannot be used for AC application.

#### 2. Do not apply a voltage exceeding the capacitor's voltage rating.

If a voltage execeeding the capacitor's voltage rating is applied, the capacitor may be damaged as leakage current increases. When using the capacitor with AC voltage superimposed on DC voltage, care must be exercised that the peak value of AC voltage does not exceed the rated voltage.

#### 3. Do not allow excessive ripple current to pass.

Use the electrolytic capacitor at current values within the permissible ripple range. If the ripple current exceeds the specified value, request capacitors for high ripple current applications.

#### 4. Ascertain the operating temperature range.

Use the electrolytic capacitors according to the specified operating temperature range. Usage at room temperature will ensure longer life.

#### 5. The electrolytic capacitor is not suitable for circuits in which charge and discharge are frequently repeated.

If used in circuits in which charge and discharge are frequently repeated, the capacitance value may drop, or the capacitor may be damaged. Please consult our engineering department for assistance in these applications.

#### 6. Apply voltage treatment to the electrolytic capacitor which has been allowed to stand for a long time.

If the electrolytic capacitor is allowed to stand for a long time, its withstand voltage is liable to drop, resulting in increased leakage current. If the rated voltage is applied to such a product, a large leakage current occurs and this generates internal heat, which damaged the capacitor. If the electrolytic capacitor is allowed to stand for a long time, therefore, use it after giving voltage treatment (Note 1). (However, no voltage treatment is required if the electrolytic capacitor is allowed to stand for less than 2 or 3 years at normal temperature.)

#### 7. Be careful of temperature and time when soldering.

When soldering a printed circuit board with various, components, care must be taken that the soldering temperature is not too high and that the dipping time is not too long. Otherwise, there will be adverse effects on the electrical characteristics and insulation sleeve of electrolytic capacitors in the case of small-sized electrolytic capacitors, nothing abnormal will occur if dipping is performed at less than 260°C for less than 10 seconds.

#### 8. Do not place a soldering iron on the body of the capacitor.

The electrolytic capacitor is covered with a vinyl sleeve. If the soldering iron comes in contact with the electrolytic capacitor body during wiring, damage to the vinyl sleeve and/or case may result in defective insulation, or improper protection of the capacitor element.

#### 9. Cleaning circuit boards after soldering.

Some solvents have adverse effects on capacitors.

Please refer to the next page.

#### 10.Do not apply excessive force to the lead wires or terminals.

If excessive force is applied to the lead wires and terminals, they may be broken or their connections with the internal elements may be affected. (For strength of terminals, refer to KS C IEC 60384-4(JIS C5101-1, JIS C5101-4)

#### 11. Care should be used in selecting a storage area.

If electrolytic capacitors are exposed to high temperatures caused by such things as direct sunlight, the life of the capacitor may be adversely affected. Storage in a high humidity atmosphere may affect the solderability of lead wires and terminals.

#### 12.Surge voltage.

The surge voltage rating is the maximum DC over-voltage to which the capacitor may be subjected for short periods not exceeding approximately 30 seconds at infrequent intervals of not more than six minutes. According to KS C IEC 60384-4, the test shall be conducted 1000 cycles at room temperature for the capacitors of characteristic KS C IEC 60384-4 or at the maximum operating temperature for the capacitors of characteristics B and C of KS C IEC 60384-4 with voltage applied through a series resistance of 1000 ohms without discharge. The electrical characteristics of the capacitor after the test are specified in KS C IEC 60384-4. Unless otherwise specified, the rated surge voltage are as follows:

Rated Voltage(V)	2	4	6.3	10	16	25	35	50	63	80	100	160	200	250	315	350	400	450	500
Rated Surge Voltage(V)	2.5	5	8	13	20	32	44	63	79	100	125	200	250	300	365	400	450	500	550

Note 1 Voltage treatment ... Voltage treatment shall be performed by increasing voltage up to the capacitor's voltage rating gradually while lowering the leakage current. In this case, the impressed voltage shall be in the range where the leakage current of the electrolytic capacitor is less than specified value. Meanwhile, the voltage treatment time may be effectively shortened if the ambient temperature is increased (within the operating temperature range).

Note 2 For methods of testing, refer to KS C IEC 60384-4, (JIS C 5101-1, JIS C 5101-4)

### CLEANING CONDITIONS

Aluminum electrolytic capacitors that have been exposed to halogenated hydrocarbon cleaning and defluxing solvents are susceptible to attack by these solvents. This exposure can result in solvent penetration into the capacitors, leading to internal corrosion and potential failure.

Common type of halogenated cleaning agents are listed below.

Chemical Name	Structural Formula	Representatice Brand Name
Trichlorotrifluoroethane	C <sub>2</sub> CI <sub>3</sub> F <sub>3</sub>	Freon TF,Daiflon S-3
Fluorotrichloromethane	CCl₃F	Freon-11,Daiflon S-1
1,1,1-Trichloroethane	F <sub>2</sub> H <sub>3</sub> CI <sub>3</sub>	Chloroethane
Trichloroethylene	C₂HCl₃	Trichiene
Methyl Chloride	CH₃CI	MC

We would like to recommend you the below cleaning materials for your stable cleaning condition taking the place of previous materials.

Olsopropyl Alcohol(IPA) or Water

Cleaning method: One of immersion, ultrasonic or vapor cleaning.

Maximum cleaning time: 5 minutes(Chip type: 2 minutes)

\*Do not use AK225AES

Aluminum electrolytic capacitors are easily affected by halogen ions, particularly by chloride ions. Excessive amounts of halogen ions, if happened to enter the inside of the capacitors, will give corrosion accidents-rapid capacitance drop and vent open. The extent of corrosion accidents varies with kinds of electrolytes and seal-materials. Therefore, the prevention of halogen ion contamination is the most improtant check point for quality control in our procuction lines. At present, halogenated hydrocarboncontained organic solvents such as Trichloroethylene, 1,1,1-Trichloroethane, and Freon are used to remove flux from circuit boards.

If electroytic capacitors are cleaned with such solvents, they may gradually penetrate the seal portion and cause the eosion. When using latex-based adhesive on the capacitors rubber end seal for adhesion to a PCB, corrosion may occur depending on the kind of solvent in the adhesive. Select an adhesive as an organic solvent with dissolved polymer that is not halogenated hydrocarbon. Hot air drying is required for eliminating the solvent between the product and the PCB at 50 °C~80 °C after coating.

Followings are the penetration path of the halogenated solvent.

- (1) Penetration between the rubber and the aluminum case
- 2 Penetration between the rubber and the lead wire
- ③ Penetration through the rubber

The inside of the capacitors, the mechanism of corrosion of aluminum electrolytic capacitors by halogen ions can be explained as follows:

Halides(RX) are absorbed and diffused into the seal portion. The halides then enter the inside of the capacitors and contact with the electrolyte of the capacitors. Where by halogen ions are made free by a hydrolysis with water in the electrolyte:

$$RX + H_2O \rightarrow ROH + H^+ + X^-$$

The halogen ions (X) react with the dielectric substance(Al<sub>2</sub>O<sub>3</sub>) of aluminum electrolytic capacitors:

$$Al_2O_3 + 6H^+ + 6X^- \rightarrow 2ALX_3 + 3H_2O$$

AIX<sub>3</sub> is dissociated with water:

$$ALX_3 + 3H_2O \rightarrow AL (OH)_3 + 3H^+ + 3X^-$$

#### **\*\*MANUFACTURING SITE**

- SamYoung Electronics Co., Ltd. (Korea/China)

