## SIEMENS

## Data sheet

## 3RA2210-1FD15-2AK6



FUSELESS LOAD FEEDER REVERSING OPERATION, AC 400V, S00 3.5...5A, AC 110/120V 50/60HZ SCREW TERMINAL FOR BUSBAR SYSTEMS 60MM TYPE OF ASSIGNMENT 1,IQ = 150KA 1NC (CONTACTOR)

product brand name	SIRIUS
product designation	non-fused load feeders 3RA2
design of the product	reversing starter
manufacturer's article number	
of the supplied contactor	3RT2015-1AK62
<ul> <li>of the supplied circuit-breakers</li> </ul>	3RV2011-1FA10
<ul> <li>of the supplied RS assembly kit</li> </ul>	8US1250-5AS10
<ul> <li>of the supplied NS assembly kit</li> <li>of the supplied busbar adapter</li> </ul>	
	8US1251-5DS10 2R41021 1D400
of the supplied link module	<u>3RA1921-1DA00</u>
General technical data	000
size of the circuit-breaker	S00
size of load feeder	S00
product extension auxiliary switch	Yes
insulation voltage with degree of pollution 3 at AC rated value	690 V
degree of pollution	3
surge voltage resistance rated value	6 kV
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (switching cycles) of contactor typical	30 000 000
type of assignment	1
Substance Prohibitance (Date)	10/01/2009
Ambient conditions	
ambient temperature	
<ul> <li>during operation</li> </ul>	-20 +60 °C
<ul> <li>during storage</li> </ul>	-50 +80 °C
during transport	-50 +80 °C
Main circuit	
number of poles for main current circuit	3
design of the switching contact	electromechanical
adjustable current response value current of the current-dependent overload release	3.5 5 A
operating voltage	
rated value	690 V
<ul> <li>at AC-3 rated value maximum</li> </ul>	690 V
operating frequency rated value	50 60 Hz
operational current at AC-3 at 400 V rated value	3.6 A
operating power at AC-3	
at 400 V rated value	1 500 W
• at 500 V rated value	2 200 W

<ul> <li>at 690 V rated value</li> </ul>	3 000 W
Control circuit/ Control	
control supply voltage at AC	
at 50 Hz rated value	110 V
at 50 Hz rated value	120 V
	4.2 VA
apparent holding power of magnet coil at AC	4.2 VA
Protective and monitoring functions	01 4000 40
trip class	CLASS 10
design of the overload release	thermal (bimetallic)
response value current of instantaneous short-circuit trip unit	65 A
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	
<ul> <li>at 480 V rated value</li> </ul>	4.8 A
• at 600 V rated value	4.55 A
yielded mechanical performance [hp]	
<ul> <li>for single-phase AC motor</li> </ul>	
— at 110/120 V rated value	0.17 hp
— at 230 V rated value	0.5 hp
<ul> <li>for 3-phase AC motor</li> </ul>	
— at 200/208 V rated value	1 hp
— at 220/230 V rated value	1 hp
— at 460/480 V rated value	3 hp
— at 575/600 V rated value	3 hp
Short-circuit protection	
product function short circuit protection	Yes
design of the short-circuit trip	magnetic
conditional short-circuit current (lq)	
<ul> <li>at 690 V according to IEC 60947-4-1 rated value</li> </ul>	4 000 A
<ul> <li>at 400 V according to IEC 60947-4-1 rated value</li> </ul>	153 000 A
<ul> <li>at 500 V according to IEC 60947-4-1 rated value</li> </ul>	100 000 A
Installation/ mounting/ dimensions	
mounting position	vertical
	Vortical
fastening method	for snapping onto 60 mm busbar systems
fastening method height	for snapping onto 60 mm busbar systems
height	200 mm
height width	200 mm 90 mm
height width depth	200 mm
height width depth required spacing	200 mm 90 mm
height         width         depth         required spacing         • for grounded parts	200 mm 90 mm 155.1 mm
height         width         depth         required spacing         • for grounded parts         — forwards	200 mm 90 mm 155.1 mm 0 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards	200 mm 90 mm 155.1 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards         — backwards         — backwards	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 0 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards         — upwards         • for live parts         — norwards         — upwards         • upwards         • for live parts         — upwards         — upwards	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 0 mm 20 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards         — upwards         • for live parts         — forwards         — downwards         — downwards         — upwards         — upwards         — upwards         — downwards	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 20 mm 10 mm 20 mm 10 mm 10 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards         — downwards         • for live parts         — forwards         — downwards         — at the side         — downwards         — at the side         — upwards         — at the side	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 0 mm 20 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards         — backwards         — downwards         • for live parts         — forwards         — upwards         — at the side         — downwards         — at the side         — downwards         — at the side         Connections/ Terminals	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 0 mm 0 mm 10 mm 9 mm 10 mm 9 mm 10 mm 20 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards         — backwards         — ownwards         • for live parts         — forwards         — backwards         — upwards         — at the side         — downwards         — at the side         Connections/ Terminals         type of electrical connection for main current circuit	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 20 mm 10 mm 20 mm 10 mm 10 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards         — backwards         — upwards         — ownwards         — at the side         — downwards         — at the side         — upwards         — at the side         Connections/ Terminals         type of electrical connection for main current circuit         type of connectable conductor cross-sections	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 20 mm 10 mm 20 mm 9 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards         — backwards         — of orwards         • for live parts         — forwards         — backwards         — upwards         — downwards         — at the side         Connections/ Terminals         type of electrical connection for main current circuit         type of connectable conductor cross-sections         • for main contacts stranded	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 20 mm 9 mm 10 mm 0 mm 0 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards         — backwards         — upwards         — forwards         — downwards         • for live parts         — forwards         — upwards         — upwards         — at the side         Connections/ Terminals         type of electrical connection for main current circuit         type of connectable conductor cross-sections         • for main contacts stranded         • at AWG cables for main contacts	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 0 mm 0 mm 0 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm 20 mm 10 mm 20 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards         — backwards         — upwards         — backwards         — upwards         — downwards         — at the side         Connections/ Terminals         type of electrical connection for main current circuit         type of connectable conductor cross-sections         • for main contacts stranded         • at AWG cables for main contacts         connectable conductor cross-section for main contacts	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 20 mm 9 mm 10 mm 0 mm 0 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards         — backwards         — of nive parts         — forwards         — backwards         — upwards         — downwards         — at the side         Connections/ Terminals         type of electrical connection for main current circuit         type of connectable conductor cross-sections         • for main contacts stranded         • at AWG cables for main contacts         connectable conductor cross-section for main contacts finely stranded with core end processing	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 0 mm 0 mm 0 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm 20 mm 10 mm 20 mm
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards         — backwards         — ownwards         • for live parts         — forwards         — backwards         — upwards         — backwards         — upwards         — downwards         — at the side         Connections/ Terminals         type of electrical connection for main current circuit         type of connectable conductor cross-sections         • for main contacts stranded         • at AWG cables for main contacts         connectable conductor cross-section for main contacts finely stranded with core end processing         Safety related data	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 0 mm 0 mm 20 mm 10 mm 9 mm 10 mm 10 mm 10 mm 9 mm 10 mm 1
height         width         depth         required spacing         • for grounded parts         — forwards         — backwards         — upwards         — at the side         — downwards         • for live parts         — forwards         — backwards         — of nive parts         — forwards         — backwards         — upwards         — downwards         — at the side         Connections/ Terminals         type of electrical connection for main current circuit         type of connectable conductor cross-sections         • for main contacts stranded         • at AWG cables for main contacts         connectable conductor cross-section for main contacts finely stranded with core end processing	200 mm 90 mm 155.1 mm 0 mm 0 mm 20 mm 9 mm 10 mm 0 mm 0 mm 0 mm 0 mm 20 mm 10 mm 20 mm 10 mm 20 mm 10 mm 20 mm 20 mm 10 mm 20 mm

according to SN 3192	20					
protection class IP o 60529	on the front according	to IEC IP20				
touch protection on	the front according to	IEC 60529 finge	r-safe, for vertical conta	act from the front		
Certificates/ approval	S					
General Product Ap	proval			For use in hazard- ous locations	Declaration of Conformity	
SA CSA	<u>Confirmation</u>		EAC	K ATEX	UK CA	
Declaration of Conformity	Test Certificates		Marine / Shipping			
CE EG-Konf.	<u>Type Test Certific-</u> ates/Test Report	Special Test Certific- ate	ABS	BUREAU VERITAS	Hoyd's Register urs	
Marine / Shipping				other	Railway	
PRS	RINA	RMRS	DNV-GL	<u>Confirmation</u>	Vibration and Shock	
Further information						
	wnloadcenter (Catalo	gs, Brochures,…)				
https://www.siemens.com/ic10 Industry Mall (Online ordering system)						
https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2210-1FD15-2AK6						
Cax online generator						
http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2210-1FD15-2AK6 Service&Support (Manuals, Certificates, Characteristics, FAQs,)						
https://support.industry.siemens.com/cs/ww/en/ps/3RA2210-1FD15-2AK6						
Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros,) http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RA2210-1FD15-2AK6⟨=en						
Characteristic: Tripping characteristics, I <sup>2</sup> t, Let-through current https://support.industry.siemens.com/cs/ww/en/ps/3RA2210-1FD15-2AK6/char						
Further characteristics (e.g. electrical endurance, switching frequency) http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2210-1FD15-2AK6&objecttype=14&gridview=view1						

last modified:

12/29/2021 🖸