RLIL&N

SMD3225 Series

HSF

Description

Gas discharge tubes (GDT) use noble gasses enclosed in ceramic tubes to provide an alternate circuit path for voltage spikes. The ceramic envelope and with nickel connectors allow for high loads. SMD3225 Gas Discharge Tubes (GDT) series has a surge rating of 1kA, 8/20µs.Offered in a Squared Surface Mount package, which helps to make pick and place on PCB process easier.

This GDT series is perfectly suited for broadband equipment applications. The GDT's low off-state capacitance is compatible with high bandwidth applications and this capacitance loading value does not vary if the voltage across the GDT changes.

SMD3225 Gas Discharge Tube (GDT) series are specifically designed for protection of electrical, multimedia, and communication equipment against over voltage transients in surface mount assembly applications.

Features

- Excellent response to fast rising transients I
- I Stable breakdown voltage
- I GHz working frequency
- I 8/20µs Impulse current capability: 1KA
- I Surface Mount package
- I Non-Radioactive
- Ultra Low capacitance(<0.5pF) and insertion loss I
- I Very Small Size(EIA 1210)
- Storage and operational temperature: -40~+85°C I

Agency Approvals

Agency	Standards	Certificate No.
c FL [®] us	UL1449	E508408

Applications

- Communication Т equipment
- CATV equipment L
- Test equipment I
- Data lines I
- I Power supplies
- Telecom SLIC protection I
- Broadband equipment I
- ADSL equipment, L including ADSL2+ L
 - **XDSL** equipment
- Satellite and CATV I equipment
- L. General telecom equipment

Part Number Code



Specifications are subject to change without notice. Please refer to http://www.ruilon.com.cn for current information. Version: A3/2023-11-02 File Number: SP-GDT-003

RUIL

Gas Discharge Tubes (GDT)

SMD3225 Series

Electrical Characteristics

	DC Spark-over Voltage ^{1) 2)} @100V/S	Impulse Spark-over	Insulation Ca	Capacitance	Glow	Arc	Life Ratings					
Part Number		Voltage					Impulse	se	Alternating Discharge Current @50Hz 1S	Impulse Withstanding Voltage Capacity @10/700µS, 40W	Impulse Life @10/1000µS	
		100V/µS	1KV/µS	Resistance ³⁾	@1MHz	Voltage @10mA	Voltage @1A	Discharge Current @8/20µS				
		Max	Max	Min	Max	Typical	Typical	±5 times	1 time	5 times	±5 times	100 times
	v	v	v	GΩ	pF	v	v	KA	KA	Α	ĸv	A
SMD3225-075N	75±30%	500	600	1	0.5	60	10	1	1.5	1	6	10
SMD3225-090N	90±30%	500	600	1	0.5	60	10	1	1.5	1	6	10
SMD3225-150N	150±30%	500	600	1	0.5	60	10	1	1.5	1	6	10
SMD3225-200N	200±30%	600	700	1	0.5	60	10	1	1.5	1	6	10
SMD3225-230N	230±30%	600	700	1	0.5	60	10	1	1.5	1	6	10
SMD3225-300N	300±30%	700	800	1	0.5	60	10	1	1.5	1	6	10
SMD3225-350N	350±30%	750	850	1	0.5	60	10	1	1.5	1	6	10
SMD3225-400N	400±30%	800	900	1	0.5	135	15	1	1.5	1	6	10
SMD3225-470N	470±30%	850	950	1	0.5	135	15	1	1.5	1	6	10
SMD3225-600N	600±30%	900	1000	1	0.5	135	15	1	1.5	1	6	10
SMD3225-800N	800±30%	1200	1400	1	0.5	135	15	1	1.5	1	6	10
Glow to Arc transi	tion Current.				< <0).2A						
~0.095g												
Operation and storage temperature40~+85°C												
Climatic category (IEC 60068-1) 40/85/21												
Marking Without												
Surface treatment Matte-tin plated												
Moisture sensitivity level 4) 1												

¹⁾ At delivery AQL 0.65 level II, DIN ISO 2859.

²⁾ In ionized mode.

³⁾ Insulation Resistance Measuring Voltage:

75V~150V at DC 50V

Other at DC 100V

⁴⁾ Tests according to JEDEC J-STD-020.

Terms in accordance with ITU-T K.12, IEC 61643-311, GB/T 9043, GB/T18802.311.



Gas Discharge Tubes (GDT)

SMD3225 Series

Certifications table

Part Number	c 🔊 us
	UL1449 E508408
SMD3225-075N	•
SMD3225-090N	•
SMD3225-150N	•
SMD3225-200N	•
SMD3225-230N	•
SMD3225-300N	•
SMD3225-350N	•
SMD3225-400N	•
SMD3225-470N	•
SMD3225-600N	•
SMD3225-800N	•

Notes:

• indicates that the product has passed the certification.
-- indicates that the product is not certified.

Dimensions





Recommended Soldering Pad Layout

Symbol	Millimeters	Inches
Α	2.5±0.2	0.098±0.008
В	2.5±0.2	0.098±0.008
С	3.2±0.3	0.126±0.012
D	0.3±0.1	0.012±0.004
х	1.3	0.051
X1	3.3	0.130
Y	2.8	0.110

RUIL

SMD3225 Series

Packaging Information



W1

Reel Specifications





Direction of Unreeling

Symbol	Millimeters	Inches			
w	12±0.3	0.472±0.012			
A0	2.8±0.1	0.110±0.004			
В0	3.5±0.1	0.138±0.004			
K0	2.8±0.1	0.110±0.004			
Р	8.0±0.1	0.315±0.004			
F	5.5±0.1	0.217±0.004			
Е	1.75±0.1	0.069±0.004			
D	1.5+0.1/-0.0	0.059+0.004/-0.0			
P0	4±0.1	0.157±0.004			
P2	2±0.1	0.079±0.004			
т	0.35±0.05	0.014±0.002			
D0	13.3±0.15	0.524±0.006			
D1	330±2	12.992±0.079			
D2	100+1/-2	3.937+0.039/-0.079			
W1	12.5±0.4	0.492±0.016			

	Reel	Inner Box	Carton
Size	330×17mm	340×333×70mm	375×353×380mm
Quantity	MPQ/MOQ: 1 reel=2,500pcs	1 Inner Box=4 reels=10,000pcs	1 Carton=5 Inner boxes=50,000pcs
Photos			RILLEN MERRY BRANKERS BRANKERS

Specifications are subject to change without notice. Please refer to http://www.ruilon.com.cn for current information. Version: A3/2023-11-02 File Number: SP-GDT-003



SMD3225 Series

Soldering Parameters - Reflow Soldering (Surface Mount Devices)



Reflow Condition		Pb - Free assembly		
Preheat	-Temperature Min (T _{s(min)})	150°C		
	-Temperature Max (T _{s(max)})	200°C		
	- Time (min to max) (t _s)	60 -180 Seconds		
Average ram to peak	p up rate (Liquids Temp T _L)	3°C/second max		
T _{S(max)} to TL - Ramp-up Rate		5°C/second max		
Reflow	- Temperature (T _L) (Liquids)	217°C		
	- Time (min to max) (t _s)	60 -150 Seconds		
Peak Temper	rature (T _P)	260 +0/-5°C		
Time within 5 Temperature	5°C of actual peak (t _p)	10 - 30 Seconds		

Surface mounted components (SMD) may exhibit a temporary increase in the DC spark-over voltage after the solder reflow process. The components will recover within 24 hours. There is no quality defect nor change in protection levels during the temporary change in DC spark-over voltage.

Terms and definitions

NO.	Item	Definitions
		A gap, or several gaps, in an enclosed discharge medium, other than air at atmospheric pressure,
1	Gas discharge 1 tube(GDT)	designed to protect apparatus or personnel, or both, from high transient voltages. Also referred to as
		"gas tube surge arrester".
2	DC Spark-over	The voltage at which the gas discharge tube sparks over with slowly increasing d.c. voltage
	Voltage	The voltage at which the gas discharge tube sparks over with slowly increasing u.c. voltage.
3	Impulse Spark-over	The highest voltage which appears across the terminals of a gas discharge tube in the period between
5	Voltage	the application of an impulse of given wave-shape and the time when current begins to flow.
5	Arc voltage	Voltage drop across the GDT during arc current flow.
6	Glow voltage	Peak value of voltage drop across the GDT when a glow current is flowing.
	Impulse discharge	
7	current	Current impulse with a nominal virtual front time of 8 μ s and a nominal time to half-value of 20 μ s.
	8/20µs	
0	Alternating	The rms value of an approximately sinusoidal alternating current passing through the gas discharge
⁸ Discha	Discharge Current	tube.
9	Insulation	Insulation resistance shall be measured from each terminal to every other terminal of the GDT. The test
	Resistance	is performed with DC50V when normal spark-over Voltage 70~150V, others with DC100V.
10	Capacitance	The capacitance shall be measured once at 1 MHz between all terminals unless otherwise specified.

RUIL

Gas Discharge Tubes (GDT)

SMD3225 Series

Cautions and warnings

- I Do not operate surge arresters in power supply networks, whose maximum operating voltage exceeds the minimum spark-over voltage of the surge arresters.
- I Surge arresters may become hot in the event of longer periods of current stress (burn risk). In the event of overload the connectors may fail or the component may be destroyed.
- I Surge arresters must be handled with care and must not be dropped.
- I Do not continue to use damaged surge arresters.
- I The shown SMD pad dimensions represent a safe way to mount the arrester and are a recommendation of the manufacturer. During the reflow process it must be assured that no solder material reduces the insulation distance between the pads below the arrester.
- I SMD surge arresters should be soldered within 24 month after shipment.