## **ONLY FOR REFERENCE**

# Standard Spec Sheet

Mitsumi Model Name	STO-060A24AB
Mitsumi Model No.	R 667996
Operating Force	2.4N
Pcs/Reel	20,000


This specification is only for reference. If you have any questions for the details, please contact SW engineering division.

For your adopting the products, the formal supply specification will be provided.

## MITSUMI ELECTRIC CO.,LTD.

2-11-2, Tsurumaki, Tama-shi. Tokyo 206-8657 Japan.

SWITCH ENGINEERING SECTION 1049, Tateiwa, Iizuka-shi. Fukuoka 820-8533 Japan.



1823

General specification
Tactile switches

# STO series

Approved Checked Drawn

Mar-23-18 Mar-23-18 Mar-23-18

SW Eng. SW Eng. SW Eng.

Ogura Kawaguchi Inoue

Released Mar-23-18

03. Apr. '2018

DEPT

SWITCH ENG

#### 1. General

1.1. Application

This specification is applied to Tactile switches named STO series.

1.2. Operating temperature range: -40 to +85 deg-C

1.3. Storage temperature range: -25 to +85 deg-C (Product level)

-20 to +50 deg-C (Taped condition)

#### 1.4. Test conditions

Normal temperature; 5 to 35 deg-C, normal humidity; 45 to 85% RH. If any doubt arises from judgement, tests and measurements shall be conducted under the following conditions.

Temperature 20+/- 2deg-C, humidity 65+/-5% RH, and air pressure 86 to 106 kPa.

#### 2. Appearance and Construction

2.1. Dimensions: Specified on Product specifications.

2.2. Materials: Refer to Table-1.

2.3. Appearance: There shall be no defects that affect the performance of

the products such as crack, scratch, dirt, discoloration, air bubble of

ACTUATOR, and contamination.

#### 2.4. Cross section view:




Fig. 1: Cross section of product

#### Table-1

Components	Material	Note
(1) ACTUATOR	9T Nylon	
(2) COVER FILM	9T Nylon	
(3) CLICK SPRING	Stainless steel	Ag plated
(4) BASE	9T Nylon	
(5) TERMINAL	Phosphor bronze	Ag plated

#### 3. Rating

Specified on Product specification.

	_			Code	Division	File No.
I.	lon					
1.	/IS			6	66	1022
l	Ke Ke			3	00	1823
Ι				1		

Item	aracteristics Test conditions	Criteria
4.1. Contact	Measurements shall be made under the conditions shown in Fig. 3.	Specified on Product
resistance	<ol> <li>Load: 2 times of the specified standard operating force.</li> <li>Measurement conditions: Contact resistance meter at 20 mV Max. and 10uA to 10mA.</li> </ol>	specifications.
	2.5 mm dia.  Push direction  0.5 mm Max.  Tilt angle  90+/-2 deg  Ro.3  Perimeter  (Material: Stainless steel)  Fig. 2: Push rod  Fig. 3: Measurement conditions	ISSUED 03. Apr. '2018 SWITCH ENG DEPT
4.2. Insulation resistance	Measurements shall be made under the following conditions.  1) Applied voltage: 100 V, DC  2) Duration: 1 min.  3) Applied position: Between terminals.	50 M-ohm Min.
4.3. Withstanding voltage	Measurements shall be made under the following conditions.  1) Applied voltage: 100 V, AC (50/60 Hz)  2) Duration: 1 min.  3) Leak current: 2 mA  4) Applied position: Between terminals.	There shall be no damage and breakdown.
4.4. Bounce	Measurements shall be made under the conditions shown in Fig. 3.  Bounce time at "ON" and "OFF" shall be measured under the following conditions.  1) Circuit: Refer to Fig. 4.  2) Load: 1.5 times of the specified standard operating force.  3) Frequency of operation: 3 to 4 times/sec.  DC5 V	ON bounce: 10 ms Max. OFF bounce: 10 ms Max.

File number

#### 5. Mechanical Characteristics Test conditions Item Criteria 5.1. Measurements shall be made under the conditions shown in Specified on Operating Product Fig. 3 just after striking 10 times lightly. force 1) Measurement speed: 0.5 mm/sec. specifications. 2) Limit load to apply: 1.5 to 2 times of the specified 5.2. standard operating force. Return Force (N) force Operating force Return force → Stroke (mm) Fig. 6: Force-Stroke curve Refer to 5.1 and 5.2 for the measurement conditions. Specified on 5.3. Click ratio Click ratio = $(a - b) / a \times 100\%$ Product specifications. Force (N) 5.4. Travel а b > Stroke (mm) Travel Fig. 7 Force-Stroke curve Measurements shall be made under the conditions shown in There shall be 5.5. Stopper Fig. 3 and at returned condition. no electrical strength Load: 50 N and mechanical Duration: 15 sec. abnormality. 5.6. Measurements shall be made just after applying static load Shear under the following conditions. 1) Load: 3 N strength 2) Duration: 15 sec. Test shall be made after two times of reflow soldering. Fig. 8: Shear strength test

File number

#### 5. Mechanical Characteristics

Item	Test conditions	Criteria
5.7. Vibration resistance	Measurements shall be made after testing under the following conditions.  1) Vibration frequency range: 10 to 55 Hz 2) Amplitude: 1.5 mm (peak-to-peak) 3) Sweep ratio: 10-55-10 Hz in approx. 1 min. 4) Frequency sweep mode: Logarithmic or Liner sweep 5) Direction of vibration: 3 orthogonal directions including the direction of operation. 6) Duration: 2 hr each (6 hr in total)	There shall be no electrical and mechanical abnormality.  ISSUED  03. Apr. '2018  SWITCH ENG DEPT
5.8. Impact resistance	Measurements shall be made after testing under the following conditions.  1) Acieration: 735 m/s <sup>2</sup> 2) Duration: 6 msec 3) Test direction: 6 directions 4) Number of test: 3 times per direction (18 times in total)	There shall be no electrical and mechanical abnormality.
5.9. Solderability	Measurements shall be made under the following conditions.  1) Solder temperature: 230 +/- 5 dig-C  2) Dipping time: 3 +/- 0.5 sec.  3) Composition of solder: Sn-3.0Ag-0.5Cu  4) Soldering flux: Rosin 25%, Alcohol 75%	More than 75% of dipped part shall be covered with solder.
5.10. Soldering heat resistance	Measurements shall be made after reflow soldering under the following conditions.  1) Heating method: Far-infrared radiation heating 2) Temperature profile: As shown in below. 3) Allowable soldering process: 2 times Max.  Temp.  (deg-C)  260 230  180  90+/-30 sec  Fig. 9: Reflow soldering profile  Time (sec)	There shall be no abnormality such as marked looseness, drop-off, and assured 4. Electrical Characteristics.  Operating force: Item 5.1.

#### 5.11. Precautions for soldering

- 1) This product is designed for reflow soldering. Please do not solder manually.
- 2) Do not wash the product with solvent or the like.
- 3) The soldering conditions will be different depending on reflow soldering machines. Conditions of soldering shall be confirmed under actual production conditions.
- 4) Reflow soldering shall be performed in shorter time and at lower temperature. Otherwise click ratio may be decreased.
- 5) Please set the proper volume of solder in order to prevent soldering flux ingress and float of the products.
- 6) Please do not apply soldering flux to the terminals and mounting surface of PWB/FPC.
- 7) Note that if the load is applied to the terminals during soldering it might cause deformation and defects in electrical performance.

File number

6. Durability

tions after testing under the	Crite Contact	eria		
after testing under the	Contact	Criteria		
	Contact	Insulation		
	resistance:	resistance:		
oad or no load. cles/sec.	20 ohm Max.	10 M-ohm Mir		
mum value of specified	Bounce (ON/OFF):	Withstanding voltage:		
pecified on the product	20 msec Max.	Item 4.3.		
	Operating force:	Travel:		
	Within +/-30% of specified	Item 5.4.		
	ISS 03. Apr	SUED c. '2018 H ENG EPT		
r	roles/sec. mum value of specified pecified on the product	pecified on the product  Operating force: Within +/-30% of specified initial value.  Wicles/sec.  Bounce (ON/OFF): 20 msec Max.  Operating force: Within +/-30% of specified initial value.		

#### 7. Environmental

Item	Test conditions	Criteria
7.1.	Following the test set forth below the sample shall be left in	Contact
Humidity	normal temperature and humidity conditions for 1 hr before	resistance:
resistance	measurements are made.	1 ohm Max.
	Water drops shall be removed.	
	1) Temperature: 65+/-2 deg-C, Humidity: 90 to 96% RH	Insulation
	2) Duration: 96+/-5 hr	resistance:
		10 M-ohm Min.
7.2.	Following the test set forth below the sample shall be left in	
Heat	normal temperature and humidity conditions for 1 hr before	Withstanding
resistance	measurements are made.	voltage:
	1) Temperature: 85+/-3 deg-C	Item 4.3.
	2) Duration: 96+/-5 hr	
		Bounce
7.3.	Following the test set forth below the sample shall be left in	(ON/OFF):
Cold resistance	normal temperature and humidity conditions for 1 hr before measurements are made.	20 msec Max.
	Water drops shall be removed.	Operating force:
	1) Temperature: -40+/-3 deg-C	Within +/-30%
	2) Duration: 96+/-5 hr	of specified
		initial value.
		Travel:
		Item 5.4.

File number

#### 7 Environmental

Item	Test conditions	Criteria
7.4.	Following continuous 5 cycles of the temperature cycling test	Contact
Temperature	set forth below, the sample shall be left in normal	resistance:
cycling	temaperature and humidity conditions for 1hr before	1 ohm Max.
	measurements are made.	
		Insulation
		resistance:
	85+/-2 deg-	10 M-ohm Min.
		Withstanding
	-40+/-3 deg-	voltage:
		Item 4.3.
	120 min 10 to 15 min	
	<b>→</b>	Bounce
	10 to 15 min	(ON/OFF):
	1 cycle	20 msec Max.
	1 Cycle	
	Fig. 10: Temperature cycling test conditions	Operating force:
		Within +/-30%
	ISSUED	of specified
		initial value.
	03. Apr. '2018	
	SWITCH ENG	Travel:
	DEPT	Item 5.4.
7.5.	Ingress shall be confirmed after the test under the following	There shall be
Water	conditions based on IPX7.	no ingress water
resistance	1) Depth of immersion: 1 m	inside of the
IPX7 equivalent	2) Duration of immersion: 30 min.	product.
7.6.	Ingress shall be confirmed after the test under the following	There shall be
Dust protection	conditions based on IP6X.	no ingress dust
IP6X equivalent	1) Temperature: 15 to 35 deg-C(Normal temperature)	inside of the
	Humidity: 25 to 75% RH(Normal humidity)	product.
	2) Air pressure 86 to 106 kPa.	
	3) Amount of tarc:2 kg/m <sup>3</sup> , Tarc:JIS Z8901-4	
	4) Time: 8hours	

#### 8. Use Condition

8.1. Operating temperature range: Refer to the item 1.2.

(Temperature range which the product is ON and OFF electrically.)

There shall be no freezing and condensation.

- 8.2. Using environment
  - 1) Do not expose the products to corrosive gas such as sulfur gas and salty wind.
  - 2) Visible dust must be cleared.
  - 3) Please do not apply excessive load to the products to avoid deformation and deterioration.

#### 9. Storage Condition

- 9.1. Storage temperature range: Refer to the item 1.3. There shall be no freezing and condensation.
- 9.2. Environment
  - 1) Do not expose the products to corrosive gas such as sulfur gas, and salty wind.
  - 2) Visible dust must be cleared.
  - 3) Please do not apply excessive load to the products to avoid deformation and deterioration.

File number

- 9.3. Storage method
  - 1) Products shall be packed in an airtight plastic bag and stored in cool place avoiding direct sunshine.
  - 2) Do not stack too many switches for strafe. Shall be free from high temperature and high humidity.
  - 3) Do not store the products in the state of applying load on it's operation area.
  - 4) Products should be used within six months after the date of delivery.
- 10. Precautions in Use
- 10.1. Do not clean the products with a solvent or the like.
- 10.2. Do not use the products with beyond the rated current and voltage.
- 10.3. Do not apply excessive load to the terminals and the operating part.
- 10.4. Larger static load than specified and/or shock shall not be applied to the operating part.
- 10.5. After mounting the products on PWB/FPC, please do not stack too many PWB/FPC in order to avoid excessive load to the switch mounted area.
- 10.6. The dimensions of a pattern on PWB/FPC shall refer to the recommended dimensions in Product specifications.
- 10.7. If you use this product in one of the following environmental conditions, progress of sulfaration and oxidization on the contact part (silver) will be accelerated, which may cause contact failure.

Therefore, be careful about the operation environment.

- 1) Around a sulfarate hot spring where sulfide gas is generated.
- 2) In case this product is always used in a place where exhaust gas from automobiles exist.
- 10.8. Do not push the cover film of products with something sharp.
- 10.9. Please design and assemble your unit not to apply over load to the switch.
- 10.10. Please let us know beforehand if you use other shape of pushing rod than the shape described in Fig. 2.
- 10.11. Please be careful on designing and handling especially when the switch is being built into the unit, not to add side force (static or impact) to the ACTUATOR as shown below (Fig. 11), because the ACTUATOR might deform or come off.







Fig. 11 Load and impact from side direction

- 10.12. Unless provided for otherwise, the products have been designed and manufactured for application in equipment and devices which are sold to end users in the market, including audio-visual equipment, electrical home appliances, office machines, information and communication equipment, and amusement equipment. The products are not intended for use in, and must not be used for, any application for nuclear equipment, driving equipment for aerospace or any other unauthorized use. With the exception of the abovementioned prohibited applications, please contact us (MITSUMI) and/or evaluate the total system regarding applicability for applications involving high levels of safety and liability such as medical equipment, burglar alarm equipment, disaster prevention equipment and undersea equipment. Please also incorporate fail-safe design, protection and redundant circuitry, malfunction protection, and/or fire protection into the complete system to ensure safety and reliability of the total system.
- 10.13. If you intend to use the products for automotive, please let us know beforehand.

File number

- 11. Packing Specification
- 11.1. Dimensions of carrier tape are as shown below.
- 11.2. Taping rule
  - Tape winding direction is in clockwise.
     (When pulling the tape toward, feeding holes should be located on the right side.)
  - 2) Feeding holes shall not be covered with the cover tape.

    The cover tape shall not be run off the edge of the carrier tape.
  - 3) 160 mm or more from the end of trailer tape part shall be empty.
  - 4) The leader part shall be 400 mm or more and it should include 100 mm of empty part. The leader part shall have 20 to 30 mm of un-sealed cover tape.
  - 5) The top tape of the leader part shall be stuck on the side of the reel by 30 to 50 mm using adhesive tape.
  - 6) Peeling strength of cover tape from carrier tape is 0.1 to 1.3 N at 165 to 180 deg.
  - 7) QR-code label and Mitsumi label shall be stuck on the side of the reel.
  - 8) The products shall free drop from the reversed carrier tape without cover tape after pressing at 0.1 to 0.2 N force.
  - Continuous two missing switches shall not be allowed.
     Total number of missing switches shall be 0.1% or less of the packed quantity per reel.
  - 10) The direction of products in the pockets is not specified.
  - 11) 20,000 switches shall be packed in a reel.



Α	В	С	D	Е	F	G	Н
12	1.75	5.5	4+/-0.1	4+/-0.1	2	1.5 dia +0.1/-0	1

Fig. 12 Carrier tape dimensions







Fig. 13 Taping specification


File number

### 12. Packing Specification











File number